MDS-JB730

SERVICE MANUAL

AEP Model
UK Model

Self Diagnosis Supported model

U.S. and foreign patents licensed form Dolby Laboratories Licensing Corporation.

Model Name Using Similar Mechanism	MDS-JE520
MD Mechanism Type	MDM-5D
Base Unit Type	MBU-5D
Optical Pick-up Type	KMS-260B/J1N

SPECIFICATIONS

System MiniDisc digital audio system

Disc MiniDisc

Laser Semiconductor laser (λ = 780 nm)
Emission duration: continuous

Laser output Less than 44.6 μW*

* This output is the value measured at a distance of 200 mm from the objective lens surface on the Optical Pick-up Block with 7 mm aperture.

Laser diode Material: GaAlAs

Revolutions (CLV) 400 rpm to 900 rpm

Error correction ACIRC (Advanced Cross Interleave Reed Solomon Code)

Sampling frequency 44.1 kHz

Coding ATRAC (Adaptive TRansform Acoustic Coding)

Modulation system EFM (Eight-to-Fourteen Modulation)

Number of channels 2 stereo channels

Frequency response 5 to 20,000 Hz ±0.3 dB

Signal-to-noise ratio Over 99 dB during playback

Wow and flutter Below measurable limit

Inputs

LINE (ANALOG) IN Jack type: phono
Impedance: 47 kilohms
Rated input: 500 mVrms
Minimum input: 125 mVrms

DIGITAL OPTICAL IN Connector type: square optical
Impedance: 660 nm (optical wave length)

DIGITAL COAXIAL IN Jack type: phono
Impedance: 75 ohms
Rated input: 0.5 Vp-p, ±20%

Outputs

PHONES Jack type: stereo phone
Rated output: 28 mW
Load impedance: 32 ohms

LINE (ANALOG) OUT Jack type: phono
Rated output: 2 Vrms (at 50 kilohms)
Load impedance: over 10 kilohms

DIGITAL OPTICAL OUT Connector type: square optical
Rated output: −18 dBm
Load impedance: 660 nm (optical wave length)

General

Power requirements 230 V AC, 50/60 Hz

Power consumption 17 W

Dimensions (approx.) 430 × 110 × 287 mm (w/h/d) incl. projecting parts and controls

Mass (approx.) 4.5 kg

Supplied accessories

- Audio connecting cords (2)
- Optical cable (1)
- Remote commander (remote) RM-D15M (1)
- R6 (size-AA) batteries (2)

Design and specifications are subject to change without notice.

MINIDISC DECK

SONY®

MICROFILM

SELF-DIAGNOSIS FUNCTION

The self-diagnosis function consists of error codes for customers which are displayed automatically when errors occur, and error codes which show the error history in the test mode during servicing. For details on how to view error codes for the customer, refer to the following box in the instruction manual. For details on how to check error codes during servicing, refer to the following "Procedure for using the Self-Diagnosis Function (Error History Display Mode)".

Self-Diagnosis Function

The deck's self-diagnosis function automatically checks the condition of the MD deck when an error occurs, then issues a three-digit code and an error message on the display. If the code and message alternate, find them in the following table and perform the indicated countermeasure. Should the problem persist, consult your nearest Sony dealer.

Three-digit code/Message	Cause/Remedy
C11/Protected	The inserted MD is record-protected. ➡ Take out the MD and close the record-protect slot (page 17).
C13/REC Error	The recording was not made properly. ➡ Set the deck in a stable surface, and repeat the recording procedure.
	The inserted MD is dirty (with smudges, fingerprints, etc.), scratched, or substandard in quality. ➡ Replace the disc and repeat the recording procedure.
C13/Read Error	The deck could not read the TOC on the MD properly. ➡ Take out the MD and insert it again.
C14/Toc Error	The deck could not read the TOC on the MD properly. ➡ Insert another disc. ➡ If possible, erase all the tracks on the MD (page 33).
C71/Din Unlock	The sporadic appearance of this message is caused by the digital signal being recorded. This will not affect the recording.
	While recording from a digital component connected through the DIGITAL IN connector, the digital connecting cable was unplugged or the digital component turned off. ➡ Connect the cable or turn the digital component back on.

PROCEDURE FOR USING THE SELF-DIAGNOSIS FUNCTION (ERROR HISTORY DISPLAY MODE)

Note: Perform the self-diagnosis function in the "error history display mode" in the test mode. The following describes the least required procedure. Be careful not to enter other modes by mistake. If you set other modes accidentally, press the MENU/NO button to exit the mode.

1. While pressing the [⏮ AMS ⏭] knob and [■] button, connect the power plug to the outlet, and release the [⏮ AMS ⏭] knob and [■] button.
2. Turn the [⏮ AMS ⏭] knob and when "[Service]" is displayed, press the [YES] button.
3. Turn the [⏮ AMS ⏭] knob to display "ERR DP MODE".
4. Press the [YES] button to sets the error history mode and displays "total rec".
5. Select the contents to be displayed or executed using the [⏮ AMS ⏭] knob.
6. Press the [⏮ AMS ⏭] knob to display or execute the contents selected.
7. Press the [⏮ AMS ⏭] knob another time returns to step 4.
8. Press the [MENU/NO] button to display "ERROR DP MODE" and releases the error history mode.
9. To release the test mode, press the [REPEAT] button. The unit sets into the STANDBY state, the disc is ejected, and the test mode ends.

ITEMS OF ERROR HISTORY MODE ITEMS AND CONTENTS

Selecting the Test Mode

Display	Details of History
total rec	Displays the recording time. Displayed as "r□□□□□□h". The displayed time is the total time the laser is set to the high power state. This is about 1/4 of the actual recording time. The time is displayed in decimal digits from 0h to 65535h.
total play	Displays the play time. Displayed as "p□□□□□□h". The time displayed is the total actual play time. Pauses are not counted. The time is displayed in decimal digits from 0h to 65535h.
retry err	Displays the total number of retries during recording and number of retry errors during play. Displayed as "r□□ p□□". "r" indicates the retries during recording while "p" indicates the retry errors during play. The number of retries and retry errors are displayed in hexadecimal digits from 00 to FF.
total err	Displays the total number of errors. Displayed as "total □□". The number of errors is displayed in hexadecimal digits from 00 to FF.
err history	Displays the 10 latest errors. Displayed as "0□ E@@". □ indicates the history number. The smaller the number, the more recent is the error. (00 is the latest). @@ indicates the error code. Refer to the following table for the details. The error history can be switched by turning the [⏮ AMS ⏭] knob.
er refresh	Mode which erases the "retry err", "total err", and "err history" histories. When returning the unit to the customer after completing repairs, perform this to erase the past error history. After pressing the [⏮ AMS ⏭] button and "er refresh?" is displayed, press the [YES] button to erase the history. "Complete!" will be displayed momentarily. Be sure to check the following when this mode has been executed. • The data has been erased. • The mechanism operates normally when recording and play are performed.
tm refresh	Mode which erases the "total rec" and "total play" histories. These histories serve as approximate indications of when to replace the optical pick-up. If the optical pickup has been replaced, perform this operation and erase the history. After pressing the [⏮ AMS ⏭] button and "tm refresh?" is displayed, press the [YES] button to erase the history. "Complete!" will be displayed momentarily. Be sure to check the following when this mode has been executed. • The data has been erased. • The mechanism operates normally when recording and play are performed.

Table of Error Codes

Error Code	Details of Error	Error Code	Details of Error
E00	No error	E05	FOK has deviated
E01	Disc error. PTOC cannot be read (DISC ejected)	E06	Cannot focus (Servo has deviated)
		E07	Recording retry
E02	Disc error. UTOC error (DISC not ejected)	E08	Recording retry error
		E09	Playback retry error (Access error)
E03	Loading error		
E04	Address cannot be read (Servo has deviated)	E0A	Playback retry error (C2 error)

SECTION 1
SERVICING NOTES

TABLE OF CONTENTS

SELF-DIAGNOSIS FUNCTION 2

1. SERVICING NOTES 4

2. GENERAL 11

3. DISASSEMBLY 13

4. TEST MODE 17

5. ELECTRICAL ADJUSTMENTS 22

6. DIAGRAMS

6-1. Block Diagram – SERVO Section – 31
6-2. Block Diagram – MAIN Section – 33
6-3. Note for Printed Wiring Boards and Schematic Diagrams 35
6-4. Printed Wiring Board – BD Board – 37
6-5. Schematic Diagram – BD Board (1/2) – 39
6-6. Schematic Diagram – BD Board (2/2) – 41
6-7. Schematic Diagram – SW Board – 44
6-8. Printed Wiring Board – SW Board – 44
6-9. Printed Wiring Board – MAIN Board – 45
6-10. Schematic Diagram – MAIN Board (1/2) – 47
6-11. Schematic Diagram – MAIN Board (2/2) – 49
6-12. Printed Wiring Boards – PANEL Section – 51
6-13. Schematic Diagram – PANEL Section – 53
6-14. IC Pin Function Description 58

7. EXPLODED VIEWS 65

8. ELECTRICAL PARTS LIST 69

SAFETY-RELATED COMPONENT WARNING!!

COMPONENTS IDENTIFIED BY MARK ⚠ OR DOTTED LINE WITH MARK ⚠ ON THE SCHEMATIC DIAGRAMS AND IN THE PARTS LIST ARE CRITICAL TO SAFE OPERATION. REPLACE THESE COMPONENTS WITH SONY PARTS WHOSE PART NUMBERS APPEAR AS SHOWN IN THIS MANUAL OR IN SUPPLEMENTS PUBLISHED BY SONY.

NOTES ON HANDLING THE OPTICAL PICK-UP BLOCK OR BASE UNIT

The laser diode in the optical pick-up block may suffer electrostatic break-down because of the potential difference generated by the charged electrostatic load, etc. on clothing and the human body.
During repair, pay attention to electrostatic break-down and also use the procedure in the printed matter which is included in the repair parts.
The flexible board is easily damaged and should be handled with care.

NOTES ON LASER DIODE EMISSION CHECK

The laser beam on this model is concentrated so as to be focused on the disc reflective surface by the objective lens in the optical pick-up block. Therefore, when checking the laser diode emission, observe from more than 30 cm away from the objective lens.

Laser component in this product is capable of emitting radiation exceeding the limit for Class 1.

This appliance is classified as a CLASS 1 LASER product. The CLASS 1 LASER PRODUCT MARKING is located on the rear exterior.

CAUTION : INVISIBLE LASER RADIATION WHEN OPEN AND INTERLOCKS DEFEATED. AVOID EXPOSURE TO BEAM.
ADVARSEL : USYNLIG LASERSTRÅLING VED ÅBNING NÅR SIKKERHEDSAFBRYDERE ER UDE AF FUNKTION. UNDGÅ UDSAETTELSE FOR STRÅLING.
VORSICHT : UNSICHTBARE LASERSTRAHLUNG. WENN ABDECKUNG GEÖFFNET UND SICHEREITSVERRIEGELUNG ÜBERBRÜCKT. NICHT DEM STRAHL AUSSETZEN.
VARO! : AVATTAESSA JA SUOJALUKITUS OHITETTAESSA OLET ALTTIINA NÄKYMÄTTÖMÄLLE LASERSÄTEILYLLE. ÄLÄ KATSO SÄTEESEEN.
VARNING : OSYNLING LASERSTRÅLING NÄR DENNA DEL ÄR ÖPPNAD OCH SPÄRREN ÄR URKOPPLAD. BETRAKTA EJ STRÅLEN.
ADVERSEL : USYNLIG LASERSTRÅLING NÅR DEKSEL ÅPNES OG SIKKERHEDSLÅS BRYTES. UNNGÅ EKSPONERING FOR STRÅLEN.
VIGYAZAT! : A BURKOLAT NYITÁSAKOR LÁTHATATLAN LÉZERSUGÁRVESZÉLY! KERÜLJE A BESUGÁRZÁST!

This caution label is located inside the unit.

CAUTION
Use of controls or adjustments or performance of procedures other than those specified herein may result in hazardous radiation exposure.

CAUTION

Danger of explosion if battery is incorrectly replaced.
Replace only with the same or equivalent type recommended by the manufacturer.
Discard used batteries according to the manufacturer's instructions.

ADVARSEL!

Lithiumbatteri-Eksplosionsfare ved fejlagtig håndtering.
Udskiftning må kun ske med batteri
af samme fabrikat og type.
Levér det brugte batteri tilbage til leverandøren.

ADVARSEL

Eksplosjonsfare ved feilaktig skifte av batteri.
Benytt samme batteritype eller en tilsvarende type
anbefalt av apparatfabrikanten.
Brukte batterier kasseres i henhold til fabrikantens
instruksjoner.

VARNING

Explosionsfara vid felaktigt batteribyte.
Använd samma batterityp eller en likvärdig typ som
rekommenderas av apparattillverkaren.
Kassera använt batteri enligt gällande föreskrifter.

VAROITUS

Paristo voi räjähtää, jos se on virheellisesti asennettu.
Vaihda paristo ainoastaan laitevalmistajan suosittelemaan tyyppiin.
Hävitä käytetty paristo valmistajan ohjeiden mukaisesti.

Flexible Circuit Board Repairing

- Keep the temperature of the soldering iron around 270 ˚C during repairing.
- Do not touch the soldering iron on the same conductor of the circuit board (within 3 times).
- Be careful not to apply force on the conductor when soldering or unsoldering.

Notes on chip component replacement

- Never reuse a disconnected chip component.
- Notice that the minus side of a tantalum capacitor may be damaged by heat.

JIG FOR CHECKING BD BOARD WAVEFORM

The special jig (J-2501-149-A) is useful for checking the waveform of the BD board. The names of terminals and the checking items to be performed are shown as follows.

GND : Ground
I+3V : For measuring IOP (Check the deterioration of the optical pick-up laser)
IOP : For measuring IOP (Check the deterioration of the optical pick-up laser)
TEO : TRK error signal (Traverse adjustment)
VC : Reference level for checking the signal
RF : RF signal (Check jitter)





IOP DATA RECORDING AND DISPLAY WHEN OPTICAL PICK-UP AND NON-VOLATILE MEMORY (IC171 OF BD BOARD) ARE REPLACED

The IOP value labeled on the optical pick-up can be recorded in the non-volatile memory. By recording the value, it will eliminate the need to look at the value on the optical pick-up label. When replacing the optical pick-up or non-volatile memory (IC171 of BD board), record the IOP value on the optical pick-up according to the following procedure.

Record Procedure:

1. While pressing the [⏮ AMS ⏭] knob and [■] button, connect the power plug to the outlet, and release the [⏮ AMS ⏭] knob and [■] button.
2. Turn the [⏮ AMS ⏭] knob to display "[Service]", and press the [YES] button.
3. Turn the [⏮ AMS ⏭] knob to display "Iop Write" (C28), and press the [YES] button.
4. The display becomes "Ref=@@@.@" (@ is an arbitrary number) and the numbers which can be changed will blink.
5. Input the IOP value written on the optical pick-up label.
   To select the number : Turn the [⏮ AMS ⏭] knob.
   To select the digit : Press the [⏮ AMS ⏭] knob.
6. When the [YES] button is pressed, the display becomes "Measu=@@@.@" (@ is an arbitrary number).
7. As the adjustment results are recorded for the 6 value. Leave it as it is and press the [YES] button.
8. "Complete!" will be displayed momentarily. The value will be recorded in the non-volatile memory and the display will become "Iop Write".
9. Press the [REPEAT] button to complete.

Display Procedure:

1. While pressing the [⏮ AMS ⏭] knob and [■] button, connect the power plug to the outlet, and release the [⏮ AMS ⏭] knob and [■] button.
2. Turn the [⏮ AMS ⏭] knob to display "[Service]", and press the [YES] button.
3. Turn the [⏮ AMS ⏭] knob to display "Iop Read" (C27).
4. "@@.@/##.#" is displayed and the recorded contents are displayed.
   @@.@ : indicates the IOP value on the optical pick-up label.
   ##.# : indicates the IOP value after adjustment
5. To end, press the [⏮ AMS ⏭] knob or [MENU/NO] button to display "Iop Read". Then press the [REPEAT] button.

CHECKS PRIOR TO PARTS REPLACEMENT AND ADJUSTMENTS

Before performing repairs, perform the following checks to determine the faulty locations up to a certain extent.
Details of the procedures are described in “5 Electrical Adjustments”.

	Criteria for Determination (Unsatisfactory if specified value is not satisfied)	Measure if unsatisfactory:
Laser power check (6-2 : See page 24)	• 0.9 mW power Specified value : 0.84 to 0.92 mW • 7.0 mW power Specified value : 6.8 to 7.2 mW	• Clean the optical pick-up • Adjust again • Replace the optical pick-up
	lop (at 7mW) • Labeled on the optical pickup Iop value ± 10mA	• Replace the optical pick-up
Traverse check (6-3 : See page 24)	• Traverse waveform Specified value : Below 10% offset	• Replace the optical pick-up
Focus bias check (6-4 : See page 25)	• Error rate check Specified value : For points a, b, and c C1 error : About 200 AD error : Above 00	• Replace the optical pick-up
C PLAY check (6-5 : See page 25)	• Error rate check Specified value: a. When using test disc (MDW-74/AU-1) C1 error : Below 80 AD error : Below 2 b. When using check disc (TDYS-1) C1 error : Below 50	• Replace the optical pick-up
Self-recording/playback check (6-6 : See page 25)	• CPLAY error rate check Specified value: C1 error : Below 80 AD error : Below 2	If always unsatisfactory: • Replace the overwrite head • Check for disconnection of the circuits around the overwrite head
		If occasionally unsatisfactory: • Check if the overwrite head is distorted • Check the mechanism around the sled
Temperature compensation offset check (6-1 : See page 24)	• Unsatisfactory if displayed as T=@@ (##) [NG” NG (@@, ## are both arbitrary numbers)	• Check for disconnection of the circuits around D101 (BD board) • Check the signals around IC101, IC121, CN102, CN103 (BD board)

Note:
The criteria for determination above is intended merely to determine if satisfactory or not, and does not serve as the specified value for adjustments.
When performing adjustments, use the specified values for adjustments.

RETRY CAUSE DISPLAY MODE

- In this test mode, the causes for retry of the unit during recording can be displayed on the fluorescent indicator tube. During playback, the "track mode" for obtaining track information will be set.
  This is useful for locating the faulty part of the unit.
- The following will be displayed :
  During recording and stop : Retry cause, number of retries, and number of retry errors.
  During playback : Information such as type of disc played, part played, copyright.
  These are displayed in hexadecimal.

Procedure:

1. Load a recordable disc whose contents can be erased into the unit.
2. Press the [MENU/NO] button. When "Edit Menu" is displayed on the fluorescent indicator tube, turn the [⏮ AMS ⏭] knob to display "All Erase?".
3. Press the [YES] button. (Or press the [⏮ AMS ⏭] knob)
4. When "All Erase??" is displayed on the fluorescent indicator tube, the music calendar number blinks.
5. Press the [YES] button to display "Complete!!", and press the [■] button immediately. Wait for about 15 seconds while pressing the button. (The [⏮ AMS ⏭] knob can be pressed instead of the [YES] button for the same results.)
6. When the "TOC" displayed on the fluorescent display tube goes off, release the [■] button.
7. Press the [REC ●] button to start recording. Then press the [❚❚] button and start recording.
8. To check the "track mode", press the [▷] button to start play.
9. To release the test mode, press the [I/⏻] button, and turn OFF the power. When "TOC" disappears, disconnect the power plug from the outlet.

Fig. 1 Reading the Test Mode Display (During recording and stop)

[RTs@@c##e**]
Fluorescent indicator tube display

@@ : Cause of retry
: Number of retries
** : Number of retry errors

Fig. 2 Reading the Test Mode Display (During playback)

[@@ ###** $$]
Fluorescent indicator tube display

@@ : Parts No. (name of area named on TOC)
: Cluster } Address
** : Sector }
$$: Track mode (Track information such as copyright information of each part)

Reading the Retry Cause Display

	Higher Bits				Lower Bits				Hexa-decimal	Cause of Retry	Occurring conditions
Hexadecimal	8	4	2	1	8	4	2	1			
Bit	b7	b6	b5	b4	b3	b2	b1	b0			
Binary	0	0	0	0	0	0	0	1	01	shock	When track jump (shock) is detected
	0	0	0	0	0	0	1	0	02	ader5	When ADER was counted more than five times continuously
	0	0	0	0	0	1	0	0	04	Discontinuous address	When ADIP address is not continuous
	0	0	0	0	1	0	0	0	08	DIN unlock	When DIN unlock is detected
	0	0	0	1	0	0	0	0	10	FCS incorrect	When not in focus
	0	0	1	0	0	0	0	0	20	IVR rec error	When ABCD signal level exceeds the specified range
	0	1	0	0	0	0	0	0	40	CLV unlock	When CLV is unlocked
	1	0	0	0	0	0	0	0	80	Access fault	When access operation is not performed normally

Reading the Display:
Convert the hexadecimal display into binary display. If more than two causes, they will be added.

Example

When 42 is displayed:
Higher bit : 4 = 0100 → b6
Lower bit : 2 = 0010 → b1
In this case, the retry cause is combined of "CLV unlock" and "ader5".

When A2 is displayed:
Higher bit : A = 1010 → b7+b5
Lower bit : 2 = 0010 → b1
The retry cause in this case is combined of "access fault", "IVR rec error", and "ader5".

Reading the Retry Cause Display

	Higher Bits				Lower Bits				Hexa-decimal	Details	
Hexadecimal	8	4	2	1	8	4	2	1			
Bit	b7	b6	b5	b4	b3	b2	b1	b0		When 0	When 1
Binary	0	0	0	0	0	0	0	1	01	Emphasis OFF	Emphasis ON
	0	0	0	0	0	0	1	0	02	Monaural	Stereo
	0	0	0	0	0	1	0	0	04	This is 2-bit display. Normally 01. 01:Normal audio. Others:Invalid	
	0	0	0	0	1	0	0	0	08		
	0	0	0	1	0	0	0	0	10	Audio (Normal)	Invalid
	0	0	1	0	0	0	0	0	20	Original	Digital copy
	0	1	0	0	0	0	0	0	40	Copyright	No copyright
	1	0	0	0	0	0	0	0	80	Write prohibited	Write allowed

Reading the Display:
Convert the hexadecimal display into binary display. If more than two causes, they will be added.

Example When 84 is displayed:
Higher bit : 8 = 1000 ⟶ b7
Lower bit : 4 = 0100 ⟶ b2
In this case, as b2 and b7 are 1 and others are 0, it can be determined that the retry cause is combined of “emphasis OFF”, “monaural”, “original”, “copyright exists”, and “write allowed”.

Example When 07 is displayed:
Higher bit : 0 = 1000 ⟶ All 0
Lower bit : 7 = 0111 ⟶ b0+b1+b2
In this case, as b0, b1, and b2 are 1 and others are 0, it can be determined that the retry cause is combined of “emphasis ON”, “stereo”, “original”, “copyright exists”, and “write prohibited”.

Hexadecimal ⟶ Binary Conversion Table

Hexadecimal	Binary	Hexadecimal	Binary
0	0000	8	1000
1	0001	9	1001
2	0010	A	1010
3	0011	B	1011
4	0100	C	1100
5	0101	D	1101
6	0110	E	1110
7	0111	F	1111

SECTION 2
GENERAL

This section is extracted from instruction manual.

Front Panel Parts Descriptions



1 **I/⏻ (power) switch (16, 24, 48, 50)**
Press to turn on the deck. When you turn on the deck, the STANDBY indicator turns off. When you press the switch again, the deck turns off and the indicator lights up.

2 **PITCH CONTROL button (14, 41, 42)**
Press to set the MD playback speed (pitch). When you've set the pitch to a value other than "0" (factory setting), the button lights amber during play.

3 **REPEAT button (26, 27)**
Press to play tracks repeatedly.

4 **TIME button (12-14, 18, 23)**
Press to display the remaining time.

5 **Remote sensor (4)**
Point the remote towards this sensor (▣) for remote operations.

6 **Display window (12-14, 18, 37, 41)**
Shows various information.

7 **MENU/NO button (19, 20, 28-40, 43, 51)**
Press to display "Edit Menu" or "Setup Menu."

8 **AMS control (17, 19-21, 24, 25, 28-43)**
Turn to locate tracks, select the input characters, or select a menu item and a setting value.

9 **YES button (19, 20, 28-40, 43)**
Press to carry out the selected operation.

10 **REC MODE selector (16)**
Use to set the REC MODE to STEREO or MONO.

11 **INPUT selector (16, 18, 19, 48)**
Use to select the input jack (or connector) of the programme source to be recorded.

12 **REC LEVEL control (18)**
Turn to adjust the recording level.

13 **REC ● button (17, 18, 20, 23, 40)**
Press to record on the MD, monitor the input signal, or mark track numbers.

14 **■ button (17, 24, 44)**
Press to stop play or recording, or cancel the selected operation.

15 **▮▮ button (7, 17, 23, 24)**
Press to pause play or recording. Press again to resume play or recording.

16 **▷ button (7, 17, 23-25, 27, 28, 44)**
Press to start play.

17 **◀◀/▶▶ buttons (26, 28, 29, 31, 33, 34, 37)**
Press to locate a portion within a track, change the contents of a programme, or change the input character.

18 **EJECT ⏏ button (17, 18, 24)**
Press to eject the MD.

19 **CLEAR button (28, 29, 37, 52)**
Press to cancel the selection.

20 **MD insertion slot (16, 24)**
Insert the MD as illustrated below.



21 **DISPLAY/CHAR button (12, 13, 18, 28, 37)**
- Press when the deck is stopped to display disc information or the contents of a programme.
- Press during recording to display information on the track being recorded.
- Press during play to display information on the current track.
- Press during recording pause to adjust the recording level.
- Press while editing an MD to select the type of characters to be input.

22 **SCROLL button (14)**
Press to scroll the name of a track or MD.

23 **PLAY MODE button (27, 28, 44)**
Press to select Shuffle Play or Programme Play.

24 **PHONE LEVEL control (24)**
Turn to adjust the volume of the headphones.

25 **PHONES jack (24)**
Connect headphones to this jack.

26 **TIMER selector (44)**
Use to set the timer for recording (REC) or playing (PLAY). Set to OFF to turn off the timer.

Remote Parts Descriptions



1 **I/⏻ (power) switch (16, 24, 48, 50)**
Press to turn on the deck. When you turn on the deck, the STANDBY indicator on the deck turns off. When you press the switch again, the deck turns off and the indicator lights up.

2 **DISPLAY button (12, 13, 18, 28)**
Press to select the information to be displayed in the window.

SCROLL button (14)
Press to scroll the name of a track or MD.

TIME button (12-14, 18, 23)
Press to display the remaining time.

3 **Letter/number buttons (25, 28, 38)**
Press to input letters or numbers.

4 **M.SCAN button (25)**
Press to scan a track within a range of six to twenty seconds.

5 **A.SPACE button (29, 30)**
Press to insert a three-second blank space between tracks or to pause play after each track.

6 **CLEAR button (28, 29, 38, 39, 52)**
Press to cancel the selection.

7 **■ button (17, 24, 44)**
Press to stop play or recording, or cancel the selected operation.

8 **II button (17, 22, 24)**
Press to pause play or recording. Press again to resume play or recording.

9 **● button (17, 18, 20, 40)**
Press to record on the MD, monitor the input signal, or mark track numbers.

10 **MUSIC SYNC button (22, 40)**
Press to start Music Synchro-recording.

11 **T.REC button (21)**
Press to start Time Machine Recording.

12 **LEVEL +/– buttons (18, 24)**
Press to adjust the recording or analog output level.

13 **FADER button (42, 43)**
Press to perform Fade-in Play/Recording or Fade-out Play/Recording.

14 **CD PLAYER II button (23)**
Press to pause the CD play. Press again to resume CD play.

CD PLAYER I◀◀/▶▶I buttons (23)
Press to locate tracks on the CD.

15 **CD-SYNC STOP button (23)**
Press to stop CD Synchro-recording.

CD-SYNC START button (22, 23)
Press to start CD Synchro-recording.

CD-SYNC STANDBY button (22, 23)
Press to enter standby for CD Synchro-recording.

16 **◀◀/▶▶ buttons (26-29, 33, 34, 38)**
Press to locate a portion within a track, change the contents of a programme, or shift the cursor to the right.

17 **I◀◀/▶▶I buttons (17, 19, 20, 24, 25, 28-30, 32-36, 38-40, 43)**
Press to locate tracks or select a menu item and a setting value.

18 **▷ button (17, 24, 25, 27, 28, 44)**
Press to start play.

19 **NAME button (38, 39)**
Press to add the name or change the name of a track or MD.

CHAR button (38)
Press to select the type of characters to be input.

NUM button (38)
Press to input numbers.

20 **REPEAT button (26, 27)**
Press to play tracks repeatedly.

A↔B button (27)
Press to select Repeat A-B Play.

21 **CONTINUE button (27, 28, 44)**
Press to resume normal play.

SHUFFLE button (27, 44)
Press to select Shuffle Play.

PROGRAM button (28, 44)
Press to select Programme Play.

22 **MENU/NO button (19, 20, 28-36, 38-40, 43, 51)**
Press to display "Edit Menu" or "Setup Menu."

YES button (19, 20, 28-36, 38-40, 43)
Press to carry out the selected operation.

23 **EJECT ⏏ button (17, 18, 24)**
Press to eject the MD.

SECTION 3
DISASSEMBLY

Note: Follow the disassembly procedure in the numerical order given.

CASE (4095269)



FRONT PANEL SECTION



MAIN BOARD


❶ wire (flat type) (21 core) (CN341)
❶ wire (flat type) (23 core) (CN501)
❷ power cord connector (CN901)
❶ wire (flat type) (19 core) (CN421)
❸ four screws (PTTWH3 × 6)
❸ two screws (PTTWH3 × 6)
❷ two connectors (CN502, 770)
❺ MAIN board
❹ five screws (BVTP3 × 8)

MECHANISM DECK SECTION (MDM-5D)


❹ four screws (BVTTWH M3)
❶ wire (flat type) (21 core) (CN341)
❺ Remove the mechanism deck (MDM-5D) to direction of the arrow.
❶ wire (flat type) (23 core) (CN501)
❷ connector (CN502)
❸ harness

SLIDEDR (CAM)


❼ slider (Cam)
❹ bracket (Guide L)
❶ two screws (P2.6 × 6)
❷ harness
❸ leaf spring
❺ two screws (P2.6 × 6)
❻ bracket (Guide R)
• Note for Installation of Slider A (Cam)
Set the shaft of Cam gear to be at the position in the figure.
Set the shaft of Lever (O/C) to be at the position in the figure.

BASE UNIT (MBU-5D), BD BOARD


❷ base unit (MBU-5D)
❺ flexible board (CN104)
❻ flexible board (CN101)
❶ three screws (P2.6 × 6)
❼ BD board
❹ screw (M1.7 × 4)
❸ Remove the solder (Seven portion).

SW BOARD, LOADING MOTOR (M103)



SECTION 4
TEST MODE

1. PRECAUTIONS FOR USE OF TEST MODE

- As loading related operations will be performed regardless of the test mode operations being performed, be sure to check that the disc is stopped before setting and removing it.
  Even if the [EJECT ⏏] button is pressed while the disc is rotating during continuous playback, continuous recording, etc., the disc will not stop rotating.
  Therefore, it will be ejected while rotating.
  Be sure to press the [EJECT ⏏] button after pressing the [MENU/NO] button and the rotation of disc is stopped.

1-1. Recording laser emission mode and operating buttons

- Continuous recording mode (CREC MODE)
- Laser power check mode (LDPWR CHECK)
- Laser power adjustment mode (LDPWR ADJUS)
- Traverse (MO) check (EF MO CHECK)
- Traverse (MO) adjustment (EF MO ADJUS)
- When pressing the [REC ●] button.

2. SETTING THE TEST MODE

The following are two methods of entering the test mode.

Procedure 1: While pressing the [⏮ AMS ⏭] knob and [■] button, connect the power plug to an outlet, and release the [⏮ AMS ⏭] knob and [■] button.
When the test mode is set, "[Check]" will be displayed. Turn the [⏮ AMS ⏭] knob switches between the following four groups; ⋯ ⟷ [Check] ⟷ [Adjust] ⟷ [Service] ⟷ [Develop] ⟷ ⋯.

Procedure 2: While pressing the [⏮ AMS ⏭] knob, connect the power plug to the outlet and release the [⏮ AMS ⏭] knob.
When the test mode is set, "TEMP CHECK" will be displayed. By setting the test mode using this method, only the "Check" group of method 1 can be executed.

3. RELEASING THE TEST MODE

Press the [REPEAT] button. The disc is ejected when loaded, and "Standby" display blinks, and becomes STANDBY state.

4. BASIC OPERATIONS OF THE TEST MODE

All operations are performed using the [⏮ AMS ⏭] knob, [YES] button, and [MENU/NO] button.
The functions of these buttons are as follows.

Function name	Function
⏮ AMS ⏭ knob	Changes parameters and modes
YES button	Proceeds onto the next step. Finalizes input.
MENU/NO button	Returns to previous step. Stops operations.

5. SELECTING THE TEST MODE

There are 31 types of test modes as shown below. The groups can be switched by turning the [⏮ AMS ⏭] knob. After selecting the group to be used, press the [YES] button. After setting a certain group, turning the [⏮ AMS ⏭] knob switches between these modes. Refer to "Group" in the table for details can be selected.
All items used for servicing can be treated using group S. So be carefully not to enter other groups by mistake.

Display	No.	Contents	Mark	Group (∗)
TEMP CHECK	C01	Temperature compensation offset check		C S
LDPWR CHECK	C02	Laser power check		C S
EF MO CHECK	C03	Traverse (MO) check		C S
EF CD CHECK	C04	Traverse (CD) check		C S
FBIAS CHECK	C05	Focus bias check		C S
Scurve CHECK	C06	S letter check	(X)	C
VERIFY MODE	C07	Non-volatile memory check	(X)	C
DETRK CHECK	C08	Detrack check	(X)	C
TEMP ADJUS	C09	Temperature compensation offset adjustment		A S
LDPWR ADJUS	C10	Laser power adjustment		A S
EF MO ADJUS	C11	Traverse (MO) adjustment		A S
EF CD ADJUS	C12	Traverse (CD) adjustment		A S
FBIAS ADJUS	C13	Focus bias adjustment		A S
EEP MODE	C14	Non-volatile memory control	(X) (!)	D
MANUAL CMD	C15	Command transmission	(X)	D
SVDATA READ	C16	Status display	(X)	D
ERR DP MODE	C17	Error history display, clear		S
SLED MOVE	C18	Sled check	(X)	D
ACCESS MODE	C19	Access check	(X)	D
0920 CHECK	C20	Outermost circumference check	(X)	D
HEAD ADJUST	C21	Head position check	(X)	D
CPLAY2MODE	C22	Same functions as CPLAY MODE	(X)	D
CREC 2MODE	C23	Same functions as CREC MODE	(X)	D
ADJ CLEAR	C24	Initialization of non-volatile memory of adjustment value		A S
AG Set (MO)	C25	Auto gain output level adjustment (MO)		A S
AG Set (CD)	C26	Auto gain output level adjustment (CD)		A S
Iop Read	C27	IOP data display		C S
Iop Write	C28	IOP data write		A S
530 ******	C29	Microprocessing version display		C S
CPLAY MODE	C30	Continuous playback mode		C A S D
CREC MODE	C31	Continuous recording mode		C A S D

Group (∗)
C: Check A: Adjust
S: Service D: Develop

- For details of each adjustment mode, refer to "5. Electrical Adjustments".
  For details of "ERR DP MODE", refer to "Self-Diagnosis Function" on page 2.
- If a different mode has been selected by mistake, press the [MENU/NO] button to release that mode.
- Modes with (X) in the Mark column are not used for servicing and therefore are not described in detail. If these modes are set accidentally, press the [MENU/NO] button to release the mode immediately. Be especially careful not to set the modes with (!) as they will overwrite the non-volatile memory and reset it, and as a result, the unit will not operate normally.

5-1. Operating the Continuous Playback Mode

1. Entering the continuous playback mode

(1) Set the disc in the unit. (Whichever recordable discs or discs for playback only are available.)
(2) Turn the [⏮ AMS ⏭] knob and display "CPLAY MODE" (C30).
(3) Press the [YES] button to change the display to "CPLAY MID".
(4) When access completes, the display changes to "C = ▯▯▯▯ AD = ▯▯".
Note: The numbers "▯" displayed show you error rates and ADER.

2. Changing the parts to be played back

(1) Press the [YES] button during continuous playback to change the display as below.

"CPLAY MID" → "CPLAY OUT" → "CPLAY IN" →

When pressed another time, the parts to be played back can be moved.

(2) When access completes, the display changes to "C = ▯▯▯▯ AD = ▯▯".
Note: The numbers "▯" displayed show you error rates and ADER.

3. Ending the continuous playback mode

(1) Press the [MENU/NO] button. The display will change to "CPLAY MODE".
(2) Press the [EJECT ⏏] button and take out the disc.
Note: The playback start addresses for IN, MID, and OUT are as follows.

IN	40h cluster
MID	300h cluster
OUT	700h cluster

5-2. Operating the Continuous Recording Mode (Use only when performing self-recording/palyback check.)

1. Entering the continuous recording mode

(1) Set a recordable disc in the unit.
(2) Turn the [⏮ AMS ⏭] knob and display "CREC MODE".
(3) Press the [YES] button to change the display to "CREC MID" (C31).
(4) When access completes, the display changes to "CREC (▯▯▯▯" and "**REC**" lights up.
Note: The numbers "▯" displayed shows you the recording position addresses.

2. Changing the parts to be recorded

(1) When the [YES] button is pressed during continuous recording, the display changes as below.

"CREC MID" → "CREC OUT" → "CREC IN" →

When pressed another time, the parts to be recorded can be changed. "**REC**" goes off.

(2) When access completes, the display changes to "CREC (▯▯▯▯" and "**REC**" lights up.
Note: The numbers "▯" displayed shows you the recording position addresses.

3. Ending the continuous recording mode

(1) Press the [MENU/NO] button. The display changes to "CREC MODE" and "**REC**" goes off.
(2) Press the [EJECT ⏏] button and take out the disc.
Note 1: The recording start addresses for IN, MID, and OUT are as follows.

IN	40h cluster
MID	300h cluster
OUT	700h cluster

Note 2: The [MENU/NO] button can be used to stop recording anytime.
Note 3: Do not perform continuous recording for long periods of time above 5 minutes.
Note 4: During continuous recording, be careful not to apply vibration.

5-3. Non-Volatile Memory Mode (EEP MODE)

This mode reads and writes the contents of the non-volatile memory.
It is not used in servicing. If the unit entered this mode accidentally, press the [MENU/NO] button immediately to release it.

6. FUNCTIONS OF OTHER BUTTONS

Function	Contents
▷	Sets continuous playback when pressed in the STOP state. When pressed during continuous playback, the tracking servo turns ON/OFF.
■	Stops continuous playback and continuous recording.
▶▶	The sled moves to the outer circumference only when this is pressed.
◀◀	The sled moves to the inner circumference only when this is pressed.
SCROLL	Switches between the pit and groove modes when pressed.
PLAY MODE	Switches the spindle servo mode (CLV-S ⟷ CLV-A).
DISPLAY/CHAR	Switches the displayed contents each time the button is pressed
EJECT ⏏	Ejects the disc
REPEAT	Releases the test mode

7. TEST MODE DISPLAYS

Each time the DISPLAY/CHAR button is pressed, the display changes in the following order.



1. Mode display

Displays “TEMP ADJUS”, “CPLAYMODE”, etc.

2. Error rate display

Displays the error rate in the following way.

C = □□□□ AD = □□

C = Indicates the C1 error.

AD = Indicates ADER.

3. Address display

The address is displayed as follows. (MO: recordable disc, CD: playback only disc)

Press the SCROLL button to switches between the groove display and pit display.

h = □□□□ s = □□□□ (MO pit and CD)

h = □□□□ a = □□□□ (MO groove)

h = Indicates the header address.

s = Indicates the SUBQ address.

a = Indicates the ADIP address.

Note: “–” is displayed when servo is not imposed.

4. Auto gain display (Not used in servicing)

The auto gain is displayed as follows.

AG = □□/□□[□□

5. Detrack check display (Not used in servicing)

The detrack is displayed as follows.

ADR = □□□□□□□

6. IVR display (Not used in servicing)

The IVR is displayed as follows.

[□□][□□][□□

MEANINGS OF OTHER DISPLAYS

Display	Contents	
	When Lit	When Off
►	During continuous playback (CLV: ON)	STOP (CLV: OFF)
❚❚	Tracking servo OFF	Tracking servo ON
REC	Recording mode ON	Recording mode OFF
SYNC	CLV low speed mode	CLV normal mode
A.SPACE	ABCD adjustment completed	
OVER	Tracking offset cancel ON	Tracking offset cancel OFF
B	Tracking auto gain OK	
A-	Focus auto gain OK	
TRACK	Pit	Groove
DISC	High reflection	Low reflection
SLEEP	CLV-S	CLV-A
MONO	CLV LOCK	CLV UNLOCK

SECTION 5
ELECTRICAL ADJUSTMENTS

1. PARTS REPLACEMENT AND ADJUSTMENT

- Check and adjust the mechanism deck as follows.
  The procedure changes according to the part replaced

- Abbreviation
  OP : Optical pick-up
  OWH : Overwrite head



2. PRECAUTIONS FOR CHECKING LASER DIODE EMISSION

To check the emission of the laser diode during adjustments, never view directly from the top as this may lose your eye-sight.

3. PRECAUTIONS FOR USE OF OPTICAL PICK-UP (KMS-260A)

As the laser diode in the optical pick-up is easily damaged by static electricity, solder the laser tap of the flexible board when using it. Before disconnecting the connector, desolder first. Before connecting the connector, be careful not to remove the solder. Also take adequate measures to prevent damage by static electricity. Handle the flexible board with care as it breaks easily.



Optical pick-up flexible board

4. PRECAUTIONS FOR ADJUSTMENTS

1. When replacing the following parts, perform the adjustments and checks with **O** in the order shown in the following table.

	Optical Pick-up	BD Board			
		IC171	D101	IC101, IC121	IC192
1. Initial setting of adjustment value	O	O	×	O	×
2. Recording of IOP information (Value on the optical pick-up label)	O	O	×	×	×
3. Temperature compensation offset adjustment	×	O	O	×	×
4. Laser power adjustment	O	O	×	O	O
5. Traverse adjustment	O	O	×	O	×
6. Focus bias adjustment	O	O	×	O	×
7. Error rate check	O	O	×	O	×
8. Auto gain output level adjustment	O	O	×	O	×

2. Set the test mode when performing adjustments.
   After completing the adjustments, release the test mode.
   Perform the adjustments and checks in “group S” of the test mode.
3. Perform the adjustments to be needed in the order shown.
4. Use the following tools and measuring devices.
   - Check Disc (MD) TDYS-1
     (Part No. 4-963-646-01)
   - Test Disc (MDW-74/AU-1) (Part No. 8-892-341-41)
   - Laser power meter LPM-8001 (Part No. J-2501-046-A)
     or MD Laser power meter 8010S (Part No. J-2501-145-A)
   - Oscilloscope (Measure after performing CAL of prove)
   - Digital voltmeter
   - Thermometer
   - Jig for checking BD board waveform
     (Part No. : J-2501-149-A)
5. When observing several signals on the oscilloscope, etc., make sure that VC and ground do not connect inside the oscilloscope.
   (VC and ground will become short-circuited)
6. Using the above jig enables the waveform to be checked without the need to solder.
   (Refer to Servicing Notes on page 6)
7. As the disc used will affect the adjustment results, make sure that no dusts nor fingerprints are attached to it.

Laser power meter

When performing laser power checks and adjustment (electrical adjustment), use of the new MD laser power meter 8010S (Part No. J-2501-145-A) instead of the conventional laser power meter is convenient.
It sharply reduces the time and trouble to set the laser power meter sensor onto the objective lens of optical pick-up.

5. CREATING CONTINUOUSLY-RECORDED DISC

* This disc is used in focus bias adjustment and error rate check. The following describes how to create a continuous recording disc.

1. Insert a disc (blank disc) commercially available.
2. Turn the [⏮ AMS ⏭] knob and display “CREC MODE”. (C31)
3. Press the [YES] button again to display “CREC MID”. Display “CREC (0300)” and start to recording.
4. Complete recording within 5 minutes.
5. Press the [MENU/NO] button and stop recording .
6. Press the [EJECT ⏏] button and remove the disc.

The above has been how to create a continuous recorded data for the focus bias adjustment/check and MO error rate check.

Note :

- Be careful not to apply vibration during continuous recording.

6. CHECK PRIOR TO REPAIRS

These checks are performed before replacing parts according to "approximate specifications" to determine the faulty locations. For details, refer to "Checks Prior to Parts Replacement and Adjustments" (See page 8).

6-1. Temperature Compensation Offset Check

When performing adjustments, set the internal temperature and room temperature of 22 °C to 28 °C.

Checking Procedure:

1. Turn the [⏮ AMS ⏭] knob to display "TEMP CHECK" (C01).
2. Press the [YES] button.
3. "T=@@(##) [OK" should be displayed. If "T=@@ (##) [NG" is displayed, it means that the results are bad.
   (@@ indicates the current value set, and ## indicates the value written in the non-volatile memory)

6-2. Laser Power Check

Before checking, check the IOP value of the optical pick-up. (Refer to 8. Recording and Displaying IOP Information)

Connection :



Checking Procedure:

1. Set the laser power meter on the objective lens of the optical pick-up. (When it cannot be set properly, press the [◀◀] button or [▶▶] button to move the optical pick-up)
   Connect the digital voltmeter to CN110 pin ⑤ (I+3V) and CN110 pin ④ (IOP) on the BD board.
2. Then, turn the [⏮ AMS ⏭] knob to display "LDPWR CHECK" (C02).
3. Press the [YES] button once to display "LD 0.9 mW $ ▯▯". Check that the reading of the laser power meter become 0.84 to 0.92 mW.
4. Press the [YES] button once more to display "LD 7.0 mW $ ▯▯". Check that the reading the laser power meter and digital voltmeter satisfy the specified value.

Specified Value:

Laser power meter reading: 7.0 ± 0.2 mW
Digital voltmeter reading : Value on the optical pick-up label ±10%

(Optical pick-up label)



IOP=82.5 mA in this case
IOP (mA) = Digital voltmeter reading (mV)/1 (Ω)

5. Press the [MENU/NO] button to display "LDPWR CHECK" and stop the laser emission.
   (The [MENU/NO] button is effective at all times to stop the laser emission)

Note 1: After step 4, each time the [YES] button is pressed, the display will be switched "LD 0.7 mW $ ▯▯", "LD 6.2 mW $ ▯▯", and "LD Wp ホセイ $ ▯▯". Nothing needs to be performed here.

6-3. Traverse Check

Note 1: Data will be erased during MO reading if a recorded disc is used in this adjustment.
Note 2: If the traverse waveform is not clear, connect the oscilloscope as shown in the following figure so that it can be seen more clearly.



Connection :



Checking Procedure:

1. Connect an oscilloscope to CN110 pin ③ (TEO) and CN110 pin ① (VC) on the BD board.
2. Load a disc (any available on the market). (Refer to Note 1)
3. Press the [▶▶] button to move the optical pick-up outside the pit.
4. Turn the [⏮ AMS ⏭] knob to display "EF MO CHECK" (C03).
5. Press the [YES] button to display "EFB = ▯▯ MO-R".
   (Laser power READ power/Focus servo ON/tracking servo OFF/spindle (S) servo ON)
6. Observe the waveform of the oscilloscope, and check that the specified value is satisfied. Do not turn the [⏮ AMS ⏭] knob.
   (Read power traverse checking)

Traverse Waveform



Specified value : Below 10% offset value

$$\text{Offset value (\%)} = \frac{|A - B|}{2\,(A + B)} \times 100$$

7. Press the [YES] button to display "EFB = ▯▯ MO-W".
8. Observe the waveform of the oscilloscope, and check that the specified value is satisfied. Do not turn the [⏮ AMS ⏭] knob.
   (Write power traverse checking)

Traverse Waveform



Specified value : Below 10% offset value

$$\text{Offset value (\%)} = \frac{|A - B|}{2\,(A + B)} \times 100$$

9. Press the [YES] button to display "EFB = □□ MO-P". Then, the optical pick-up moves to the pit area automatically and servo is imposed.
10. Observe the waveform of the oscilloscope, and check that the specified value is satisfied. Do not turn the [⏮ AMS ⏭] knob.

Traverse Waveform



Specified value : Below 10% offset value

$$\text{Offset value (\%)} = \frac{|A - B|}{2\,(A + B)} \times 100$$

11. Press the [YES] button to display "EF MO CHECK" The disc stops rotating automatically.
12. Press the [EJECT ⏏] button and take out the disc.
13. Load the check disc (MD) TDYS-1.
14. Turn the [⏮ AMS ⏭] knob and display "EF CD CHECK" (C04).
15. Press the [YES] button to display "EFB = □□ CD". Servo is imposed automatically.
16. Observe the waveform of the oscilloscope, and check that the specified value is satisfied. Do not turn the [⏮ AMS ⏭] knob.

Traverse Waveform



Specified value : Below 10% offset value

$$\text{Offset value (\%)} = \frac{|A - B|}{2\,(A + B)} \times 100$$

17. Press the [YES] button to display "EF CD CHECK".
18. Press the [EJECT ⏏] button and take out the check disc.

6-4. Focus Bias Check

Change the focus bias and check the focus tolerance amount.

Checking Procedure :

1. Load the test disk (MDW-74/AU-1).
2. Turn the [⏮ AMS ⏭] knob to display "CPLAY MODE" (C30).
3. Press the [YES] button twice to display "CPLAY MID".
4. Press the [MENU/NO] button when "C = □□□□ AD = □□" is displayed.
5. Turn the [⏮ AMS ⏭] knob to display "FBIAS CHECK" (C05).
6. Press the [YES] button to display "□□□□/□□ c = □□". The first four digits indicate the C1 error rate, the two digits after [/] indicate ADER, and the 2 digits after [c =] indicate the focus bias value. Check that the C1 error is below 50 and ADER is below 2.
7. Press the [YES] button to display "□□□□/□□ b = □□". Check that the C1 error is about 200 and ADER is below 2.
8. Press the [YES] button to display "□□□□/□□ a = □□". Check that the C1 error is about 200 and ADER is below 2.
9. Press the [MENU/NO] button, then press the [EJECT ⏏] button and take out the test disc.

6-5. C PLAY Checking

MO Error Rate Check

Checking Procedure :

1. Load the test disk (MDW-74/AU-1).
2. Turn the [⏮ AMS ⏭] knob to display "CPLAY MODE" (C30).
3. Press the [YES] button to display "CPLAY MID".
4. The display changes to "C = □□□□ AD = □□".
5. If the C1 error rate is below 80, check that ADER is below 2.
6. Press the [MENU/NO] button to stop playback, then press the [EJECT ⏏] button and take out the test disc.

CD Error Rate Check

Checking Procedure :

1. Load the check disc (MD) TDYS-1.
2. Turn the [⏮ AMS ⏭] knob to display "CPLAY MODE" (C30).
3. Press the [YES] button twice to display "CPLAY MID".
4. The display changes to "C = □□□□ AD = □□".
5. Check that the C1 error rate is below 50.
6. Press the [MENU/NO] button to stop playback, then press the [EJECT ⏏] button and take out the check disc.

6-6. Self-Recording/playback Check

Prepare a continuous recording disc using the unit to be repaired and check the error rate.

Checking Procedure :

1. Load a recordable disc (blank disc).
2. Turn the [⏮ AMS ⏭] knob to display "CREC MODE" (C31).
3. Press the [YES] button to display "CREC MID".
4. When recording starts, light up " **REC** " and display "CREC @@@@" (@@@@ is the address).
5. About 1 minute later, press the [MENU/NO] button to stop continuous recording.
6. Turn the [⏮ AMS ⏭] knob to display "CPLAY MODE" (C30).
7. Press the [YES] button to display "CPLAY MID".
8. "C = □□□□ AD = □□" will be displayed.
9. Check that the C1 error becomes below 80 and the AD error below 2.
10. Press the [MENU/NO] button to stop playback, then press the [EJECT ⏏] button and take out the disc.

7. INITIAL SETTING OF ADJUSTMENT VALUE

Note:
Mode which sets the adjustment results recorded in the non-volatile memory to the initial setting value. However the results of the temperature compensation offset adjustment will not change to the initial setting value.
If initial setting is performed, perform all adjustments again excluding the temperature compensation offset adjustment.
For details of the initial setting, refer to "4. Precautions on Adjustments" and execute the initial setting before the adjustment as required.

Setting Procedure :
1. Turn the [⏮ AMS ⏭] knob to display "ADJ CLEAR" (C24).
2. Press the [YES] button. "Complete!" will be displayed momentarily and initial setting will be executed, after which "ADJ CLEAR" will be displayed.

8. RECORDING AND DISPLAYING THE IOP INFORMATION

The IOP data can be recorded in the non-volatile memory. The IOP value on the optical pick-up label and the IOP value after the adjustment will be recorded. Recording these data eliminates the need to read the label on the optical pick-up.

Recording Procedure :
1. Turn the [⏮ AMS ⏭] knob to display "Iop Write" (C28), and press the [YES] button.
2. The display becomes Ref=@@@.@ (@ is an arbitrary number) and the numbers which can be changed will blink.
3. Input the IOP value on the optical pick-up label.
   To select the number : Turn the [⏮ AMS ⏭] knob.
   To select the digit : Press the [⏮ AMS ⏭] knob
4. When the [YES] button is pressed, the display becomes "Measu=@@@.@" (@ is an arbitrary number).
5. As the adjustment results are recorded for the 6 value. Leave it as it is and press the [YES] button.
6. "Complete!" will be displayed momentarily. The value will be recorded in the non-volatile memory and the display will become "Iop Write".

Display Procedure :
1. Turn the [⏮ AMS ⏭] knob to display "Iop Read"(C27).
2. "@@.@/##.#" is displayed and the recorded contents are displayed.
   @@.@ indicates the IOP value on the optical pick-up label.
   ##.# indicates the IOP value after adjustment
3. To end, press the [⏮ AMS ⏭] button or [MENU/NO] button to display "Iop Read".

9. TEMPERATURE COMPENSATION OFFSET ADJUSTMENT

Save the temperature data at that time in the non-volatile memory as 25 ˚C reference data.

Note :
1. Usually, do not perform this adjustment.
2. Perform this adjustment in an ambient temperature of 22 ˚C to 28 ˚C. Perform it immediately after the power is turned on when the internal temperature of the unit is the same as the ambient temperature of 22 ˚C to 28 ˚C.
3. When D101 has been replaced, perform this adjustment after the temperature of this part has become the ambient temperature.

Adjusting Procedure :
1. Turn the [⏮ AMS ⏭] knob to display "TEMP ADJUS" (C09).
2. Press the [YES] button to select the "TEMP ADJUS" mode.
3. "TEMP = ▯▯ [OK" and the current temperature data will be displayed.
4. To save the data, press the [YES] button.
   When not saving the data, press the [MENU/NO] button.
5. When the [YES] button is pressed, "TEMP = ▯▯ SAVE" will be displayed and turned back to "TEMP ADJUS" display then. When the [MENU/NO] button is pressed, "TEMP ADJUS" will be displayed immediately.

Specified Value :
The "TEMP = ▯▯" should be within "E0 - EF", "F0 - FF", "00 - 0F", "10 - 1F" and "20 - 2F".

10. LASER POWER ADJUSTMENT

Check the IOP value of the optical pick-up before adjustments. (Refer to 8. Recording and Displaying IOP Information)

Connection :



Adjusting Procedure :
1. Set the laser power meter on the objective lens of the optical pick-up. (When it cannot be set properly, press the [◀◀] button or [▶▶] button to move the optical pick-up)
   Connect the digital voltmeter to CN110 pin ⑤ (I+3V) and CN110 pin ④ (IOP) on the BD board.
2. Turn the [⏮ AMS ⏭] knob to display "LDPWR ADJUS" (C10).
   (Laser power : For adjustment)
3. Press the [YES] button once and display "LD 0.9 mW $ ▯▯".
4. Turn the [⏮ AMS ⏭] knob so that the reading of the laser power meter becomes 0.85 to 0.91 mW. Press the [YES] button after setting the range knob of the laser power meter, and save the adjustment results. ("LD SAVE $ ▯▯" will be displayed for a moment)
5. Then "LD 7.0 mW $ ▯▯" will be displayed.
6. Turn the [⏮ AMS ⏭] knob so that the reading of the laser power meter becomes 6.9 to 7.1 mW, press the [YES] button to save it.

Note: Do not perform the emission with 7.0 mW more than 15 seconds continuously.

7. Then, turn the [⏮ AMS ⏭] knob to display “LDPWR CHECK” (C02).
8. Press the [YES] button once to display “LD 0.9 mW $ □”. Check that the reading of the laser power meter become 0.85 to 0.91 mW.
9. Press the [YES] button once more to display “LD 7.0 mW $ □”. Check that the reading the laser power meter and digital voltmeter satisfy the specified value.
   Note down the digital voltmeter reading value.

Specified Value:
Laser power meter reading: 7.0 ± 0.2 mW
Digital voltmeter reading : Value on the optical pick-up label ±10%

(Optical pick-up label)

KMS260A
27X40
B0825

IOP=82.5 mA in this case
IOP (mA) = Digital voltmeter reading (mV)/1 (Ω)

10. Press the [MENU/NO] button to display “LDPWR CHECK” and stop the laser emission.
    (The [MENU/NO] button is effective at all times to stop the laser emission.)
11. Turn the [⏮ AMS ⏭] knob to display “Iop Write”(C28).
12. Press the [YES] button. When the display becomes Ref=@@@.@ (@ is an arbitrary number), press the [YES] button to display “Measu=@@@.@” (@ is an arbitrary number).
13. The numbers which can be changed will blink. Input the Iop value noted down at step 9.
    To select the number : Turn the [⏮ AMS ⏭] knob.
    To select the digit : Press the [⏮ AMS ⏭] knob.
14. When the [YES] button is pressed, “Complete!” will be displayed momentarily. The value will be recorded in the non-volatile memory and the display will become “Iop Write”.

Note 1: After step 4, each time the [YES] button is pressed, the display will be switched “LD 0.7 mW $ □”, “LD 6.2 mW $ □”, and “LD Wp ホセイ $ □”. Nothing needs to be performed here.

11. TRAVERSE ADJUSTMENT

Note 1: Data will be erased during MO reading if a recorded disc is used in this adjustment.
Note 2: If the traverse waveform is not clear, connect the oscilloscope as shown in the following figure so that it can be seen more clearly.



Connection :



Adjusting Procedure :
1. Connect an oscilloscope to CN110 pin ③ (TEO) and CN110 pin ① (VC) on the BD board.
2. Load a disc (any available on the market). (Refer to Note 1)
3. Press the [▶▶] button to move the optical pick-up outside the pit.
4. Turn the [⏮ AMS ⏭] knob to display “EF MO ADJUS” (C10).
5. Press the [YES] button to display “EFB = □ MO-R”.
   (Laser power READ power/Focus servo ON/tracking servo OFF/spindle (S) servo ON)
6. Turn the [⏮ AMS ⏭] knob so that the waveform of the oscilloscope becomes the specified value.
   (When the [⏮ AMS ⏭] knob is turned, the □ of “EFB= □” changes and the waveform changes.) In this adjustment, waveform varies at intervals of approx. 2%. Adjust the waveform so that the specified value is satisfied as much as possible.
   (Read power traverse adjustment)

Traverse Waveform



Specification A = B

7. Press the [YES] button and save the result of adjustment to the non-volatile memory (“EFB = □ SAV” will be displayed for a moment. Then “EFB = □ MO-W” will be displayed).

8. Turn the [⏮ AMS ⏭] knob so that the waveform of the oscilloscope becomes the specified value.
   (When the [⏮ AMS ⏭] knob is turned, the □□ of "EFB-□□" changes and the waveform changes.) In this adjustment, waveform varies at intervals of approx. 2%. Adjust the waveform so that the specified value is satisfied as much as possible.
   (Write power traverse adjustment)

Traverse Waveform



Specification A = B

9. Press the [YES] button, and save the adjustment results in the non-volatile memory. ("EFB = □□ SAV" will be displayed for a moment)
10. "EFB = □□ MO-P" will be displayed.
    The optical pick-up moves to the pit area automatically and servo is imposed.
11. Turn the [⏮ AMS ⏭] knob until the waveform of the oscilloscope moves closer to the specified value.
    In this adjustment, waveform varies at intervals of approx. 2%. Adjust the waveform so that the specified value is satisfied as much as possible.

Traverse Waveform



Specification A = B

12. Press the [YES] button, and save the adjustment results in the non-volatile memory. ("EFB = □□ SAV" will be displayed for a moment.)
    Next "EF MO ADJUS" is displayed. The disc stops rotating automatically.
13. Press the [EJECT ⏏] button and take out the disc.
14. Load the check disc (MD) TDYS-1.
15. Turn the [⏮ AMS ⏭] knob to display "EF CD ADJUS" (C12).
16. Press the [YES] button to display "EFB = □□ CD". Servo is imposed automatically.
17. Turn the [⏮ AMS ⏭] knob so that the waveform of the oscilloscope moves closer to the specified value.
    In this adjustment, waveform varies at intervals of approx. 2%. Adjust the waveform so that the specified value is satisfied as much as possible.

Traverse Waveform



Specification A = B

18. Press the [YES] button, display "EFB = □□ SAV" for a moment and save the adjustment results in the non-volatile memory.
    Next "EF CD ADJUS" will be displayed.
19. Press the [EJECT ⏏] button and take out the disc.

12. FOCUS BIAS ADJUSTMENT

Adjusting Procedure :

1. Load the continuously-recorded disc. (Refer to "5. CREATING CONTINUOUSLY-RECORDED DISC")
2. Turn the [⏮ AMS ⏭] knob to display "CPLAY MODE" (C29).
3. Press the [YES] button to display "CPLAY MID".
4. Press the [MENU/NO] button when "C = □□□□ AD = □□" is displayed.
5. Turn the [⏮ AMS ⏭] knob to display "FBIAS ADJUS" (C13).
6. Press the [YES] button to display "□□□□/□□ a = □□".
   The first four digits indicate the C1 error rate, the two digits after [/] indicate ADER, and the 2 digits after [a =] indicate the focus bias value.
7. Turn the [⏮ AMS ⏭] knob clockwise and find the focus bias value at which the C1 error rate becomes about 200 (Refer to Note 2).
8. Press the [YES] button to display "□□□□/□□ b = □□".
9. Turn the [⏮ AMS ⏭] knob counterclockwise and find the focus bias value at which the C1 error rate becomes about 200.
10. Press the [YES] button to display "□□□□/□□ c = □□".
11. Check that the C1 error rate is below 50 and ADER is 00. Then press the [YES] button.
12. If the "(□□)" in "□□ - □□ - □□ (□□)" is above 20, press the [YES] button.
    If below 20, press the [MENU/NO] button and repeat the adjustment from step 2.
13. Press the [EJECT ⏏] button and take out the disc.

Note 1: The relation between the C1 error and focus bias is as shown in the following figure. Find points A and B in the following figure using the above adjustment. The focal point position C is automatically calculated from points A and B.

Note 2: As the C1 error rate changes, perform the adjustment using the average vale.



13. ERROR RATE CHECK

13-1. CD Error Rate Check

Checking Procedure :

1. Load the check disc (MD) TDYS-1.
2. Turn the [⏮ AMS ⏭] knob and display "CPLAY MODE" (C30).
3. Press the [YES] button twice and display "CPLAY MID".
4. The display changes to "C = □□□□ AD = □□".
5. Check that the C1 error rate is below 20.
6. Press the [MENU/NO] button to stop playback, then press the [EJECT ⏏] button and take out the check disc.

13-2. MO Error Rate Check

Checking Procedure :

1. Load the continuously-recorded disc. (Refer to "5. CREATING CONTINUOUSLY-RECORDED DISC")
2. Turn the [⏮ AMS ⏭] knob to display "CPLAY MODE" (C30).
3. Press the [YES] button to display "CPLAY MID".
4. The display changes to "C1 = □□□□ AD = □□".
5. If the C1 error rate is below 50, check that ADER is 00.
6. Press the [MENU/NO] button to stop playback, then press the [EJECT ⏏] button and take out the test disc.

14. FOCUS BIAS CHECK

Change the focus bias and check the focus tolerance amount.

Checking Procedure :

1. Load the continuously-recorded disc. (Refer to "5. CREATING CONTINUOUSLY-RECORDED DISC")
2. Turn the [⏮ AMS ⏭] knob to display "CPLAY MODE" (C30).
3. Press the [YES] button twice to display "CPLAY MID".
4. Press the [MENU/NO] button when "C = □□□□ AD = □□" is displayed.
5. Turn the [⏮ AMS ⏭] knob to display "FBIAS CHECK" (C05).
6. Press the [YES] button to display "□□□□/□□ c = □□".
   The first four digits indicate the C1 error rate, the two digits after [/] indicate ADER, and the 2 digits after [c =] indicate the focus bias value.
   Check that the C1 error is below 50 and ADER is below 2.
7. Press the [YES] button and display "□□□□/□□ b = □□".
   Check that the C1 error is about 200 and ADER is below 2.
8. Press the [YES] button and display "□□□□/□□ a = □□".
   Check that the C1 error is about 200 and ADER is below 2
9. Press the [MENU/NO] button, then press the [EJECT ⏏] button and take out the disc.

Note 1: If the C1 error and ADER are above other than the specified value at points A (step 8. in the above) or B (step 7. in the above), the focus bias adjustment may not have been carried out properly. Adjust perform the beginning again.

15. AUTO GAIN CONTROL OUTPUT LEVEL ADJUSTMENT

Be sure to perform this adjustment when the optical pick-up is replaced.
If the adjustment results becomes "Adjust NG!", the optical pick-up may be faulty or the servo system circuits may be abnormal.

15-1. CD Auto Gain Control Output Level Adjustment

Adjusting Procedure :

1. Load the check disc (MD) TDYS-1.
2. Turn the [⏮ AMS ⏭] knob to display "AG Set (CD)" (C26).
3. When the [YES] button is pressed, the adjustment will be performed automatically.
   "Complete!!" will then be displayed momentarily when the value is recorded in the non-volatile memory, after which the display changes to "AG Set (CD)".
4. Press the [EJECT ⏏] button and take out the check disc.

15-2. MO Auto Gain Control Output Level Adjustment

Adjusting Procedure :

1. Load the test disc (MDW-74/AU-1).
2. Turn the [⏮ AMS ⏭] knob to display "AG Set (MO)" (C25).
3. When the [YES] button is pressed, the adjustment will be performed automatically.
   "Complete!!" will then be displayed momentarily when the value is recorded in the non-volatile memory, after which the display changes to "AG Set (MO)".
4. Press the [EJECT ⏏] button and take out the test disc.

Adjustment Location:

– BD BOARD (Side A) **–**



– BD BOARD (Side B) **–**



Note: It is useful to use the jig for checking the waveform. (Refer to Servicing Notes on page 6)

SECTION 6
DIAGRAMS

6-1. BLOCK DIAGRAM – SERVO Section –



6-2. BLOCK DIAGRAM – MAIN Section –



6-3. NOTE FOR PRINTED WIRING BOARDS AND SCHEMATIC DIAGRAMS (In addition to this, the necessary note is printed in each block)

Note on Printed Wiring Board:

- ○——— : parts extracted from the component side.
- ——— : parts extracted from the conductor side.
- ○ : Through hole.
- ▒▒▒ : Pattern from the side which enables seeing.

Caution:	
Pattern face side: (Side B)	Parts on the pattern face side seen from the pattern face are indicated.
Parts face side: (Side A)	Parts on the parts face side seen from the parts face are indicated.

- Indication of transistor.





Note on Schematic Diagram:

- All capacitors are in µF unless otherwise noted. pF: µµF 50 WV or less are not indicated except for electrolytics and tantalums.
- All resistors are in Ω and 1/4 W or less unless otherwise specified.
- % : indicates tolerance.
- △ : internal component.
- ▭ : panel designation.

Note: The components identified by mark ⚠ or dotted line with mark ⚠ are critical for safety.
Replace only with part number specified.

- B+ : B+ Line.
- B− : B– Line.
- Voltages are taken with a VOM (Input impedance 10 MΩ). Voltage variations may be noted due to normal production tolerances.
- Waveforms are taken with a oscilloscope. Voltage variations may be noted due to normal production tolerances.
- Circled numbers refer to waveforms.
- Signal path.
  - : PLAY (ANALOG OUT)
  - : PLAY (DIGITAL OUT)
  - : REC (ANALOG IN)
  - : REC (DIGITAL IN)

• **Circuit Boards Location**



6-4. PRINTED WIRING BOARD – BD Board –

• See page 36 for Circuit Boards Location.





• **Semiconductor Location**

Ref. No.	Location
D101	A-1
D181	D-3
D183	D-3
IC103	B-1
IC123	D-2
IC171	D-1
Q102	B-1
Q103	C-1
Q104	B-1

• **Semiconductor Location**

Ref. No.	Location
IC101	A-3
IC121	C-3
IC124	C-3
IC152	B-1
IC181	C-1
IC192	D-1
Q101	B-3
Q162	B-3
Q163	B-3
Q181	C-1
Q182	C-2

6-5. SCHEMATIC DIAGRAM – BD Board (1/2) –

• See page 43 for Waveforms. • See page 55 for IC Block Diagrams.



6-6. SCHEMATIC DIAGRAM – BD Board (2/2) – • See page 43 for Waveforms. • See page 55 for IC Block Diagrams.



- Voltages and waveforms are dc with respect to ground under no-signal conditions.
  no mark : STOP
  ( ) : PLAY
  < > : REC
  ∗ : Impossible to measure

The components identified by mark ⚠ or dotted line with mark ⚠ are critical for safety.
Replace only with part number specified.

• **Waveforms**
– BD Board –

❶ IC101 ①, ② (I, J) (Play mode)



❻ IC121 ㉘ (XBCK)



2.8224 MHz

❸ IC321 ⑨ (XTI)



45.1584 MHz

❷ IC101 ④ (A) (Play mode)



❼ IC121 ㉙ (FS256)



11.29 MHz

❹ IC321 ⑪ (LRCK)



44.1 kHz

❸ IC101 ⑧, ⑨ (E, F) (Play mode)



❽ IC121 ㉚ (FS4)



176.4 kHz

❺ IC321 ⑫ (BICK)



2.8224 MHz

– MAIN Board –

❹ IC121 ⑯ (OSCI)



45.158 MHz

❶ IC501 ⑮ (XIN)



10 MHz

❺ IC121 ㉗ (LRCK)



44.1 kHz

❷ IC322 ②, ③, ⑤



45.1584 MHz

– DISP board –

❶ IC771 ㊻ (OSCO)



2.618 MHz

❷ IC771 ㊺ (OSCI)



2.1 MHz

6-7. SCHEMATIC DIAGRAM – SW Board –



6-8. PRINTED WIRING BOARD – SW Board –

• See page 36 for Circuit Boards Location.



6-9. PRINTED WIRING BOARD – MAIN Board – • See page 36 for Circuit Boards Location.



• **Semiconductor Location**

Ref. No.	Location	Ref. No.	Location	Ref. No.	Location	Ref. No.	Location
D341	E-13	D431	D-3	IC301	F-13	Q287	F-11
D342	E-13	D432	D-3	IC310	B-2	Q306	F-5
D343	E-13	D439	G-4	IC321	D-13	Q401	C-2
D344	E-13	D451	F-6	IC322	C-12	Q402	C-1
D411	E-4	D452	F-6	IC431	G-4	Q403	C-1
D412	E-4	D453	G-6	IC471	B-12	Q404	C-1
D413	D-2	D454	F-6	IC501	E-9	Q471	B-12
D414	D-2	D471	B-13	IC601	G-9	Q472	B-13
D415	E-4	D851	G-7	IC611	G-10	Q851	G-7
D416	E-4			IC661	G-9		
D421	C-2	IC101	F-11				
D423	C-1	IC201	F-12	Q187	F-10		

6-10. SCHEMATIC DIAGRAM – MAIN Board (1/2) – • See page 43 for Waveforms.



• Voltages and waveforms are dc with respect to ground under no-signal conditions.
no mark : PLAY

6-11. SCHEMATIC DIAGRAM – MAIN Board (2/2) –

• See page 43 for Waveforms. • See page 57 for IC Block Diagrams.



- Voltages and waveforms are dc with respect to ground under no-signal conditions.
  no mark : PLAY

The components identified by mark ⚠ or dotted line with mark ⚠ are critical for safety.
Replace only with part number specified.

6-12. PRINTED WIRING BOARDS – PANEL Section – • See page 36 for Circuit Boards Location.



• Semiconductor Location
– DISP Board –

Ref. No.	Location
IC761	B-12
IC771	A-9
Q781	B-5
Q782	B-5

• Semiconductor Location
– PSW Board –

Ref. No.	Location
D756	A-5
D759	C-2
Q756	A-4
Q759	B-3







6-13. SCHEMATIC DIAGRAM – PANEL Section – • See page 43 for Waveforms.



1	2	3	4	5
6	7	8	9	10
11	12	13	14	15

• Voltages and waveforms are dc with respect to ground under no-signal conditions.
no mark : STOP

• **IC Block Diagrams**
– BD Board –

IC101 CXA2523AR



IC121 CXD2656R



IC152 BH6511FS-E2



– MAIN Board –

IC310 M5293L



IC431 LA5632



IC321 AK4524



IC471 LB1641



6-14. IC PIN FUNCTION DESCRIPTION

• BD BOARD IC101 CXA2523AR (RF AMP, FOCUS/TRACKING ERROR AMP)

Pin No.	Pin Name	I/O	Description
1	I	I	I-V converted RF signal I input from the optical pick-up block detector
2	J	I	I-V converted RF signal J input from the optical pick-up block detector
3	VC	O	Middle point voltage (+1.65V) generation output terminal
4 to 9	A to F	I	Signal input from the optical pick-up detector
10	PD	I	Light amount monitor input from the optical pick-up block laser diode
11	APC	O	Laser amplifier output terminal to the automatic power control circuit
12	APCREF	I	Reference voltage input terminal for setting laser power
13	GND	—	Ground terminal
14	TEMPI	I	Connected to the temperature sensor
15	TEMPR	O	Output terminal for a temperature sensor reference voltage
16	SWDT	I	Writing serial data input from the CXD2656R (IC121)
17	SCLK	I	Serial data transfer clock signal input from the CXD2656R (IC121)
18	XLAT	I	Serial data latch pulse signal input from the CXD2656R (IC121)
19	$\overline{\text{XSTBY}}$	I	Standby signal input terminal "L": standby (fixed at "H" in this set)
20	F0CNT	I	Center frequency control voltage input terminal of internal circuit (BPF22, BPF3T, EQ) input from the CXD2656R (IC121)
21	VREF	O	Reference voltage output terminal Not used (open)
22	EQADJ	I	Center frequency setting terminal for the internal circuit (EQ)
23	3TADJ	I	Center frequency setting terminal for the internal circuit (BPF3T)
24	VCC	—	Power supply terminal (+3.3V)
25	WBLADJ	I	Center frequency setting terminal for the internal circuit (BPF22)
26	TE	O	Tracking error signal output to the CXD2656R (IC121)
27	CSLED	I	Connected to the external capacitor for low-pass filter of the sled error signal
28	SE	O	Sled error signal output to the CXD2656R (IC121)
29	ADFM	O	FM signal output of the ADIP
30	ADIN	I	Receives a ADIP FM signal in AC coupling
31	ADAGC	I	Connected to the external capacitor for ADIP AGC
32	ADFG	O	ADIP duplex signal (22.05 kHz ± 1 kHz) output to the CXD2656R (IC121)
33	AUX	O	Auxiliary signal (I_3 signal/temperature signal) output to the CXD2656R (IC121)
34	FE	O	Focus error signal output to the CXD2656R (IC121)
35	ABCD	O	Light amount signal (ABCD) output to the CXD2656R (IC121)
36	BOTM	O	Light amount signal (RF/ABCD) bottom hold output to the CXD2656R (IC121)
37	PEAK	O	Light amount signal (RF/ABCD) peak hold output to the CXD2656R (IC121)
38	RF	O	Playback EFM RF signal output to the CXD2656R (IC121)
39	RFAGC	I	Connected to the external capacitor for RF auto gain control circuit
40	AGCI	I	Receives a RF signal in AC coupling
41	COMPO	O	User comparator output terminal Not used (open)
42	COMPP	I	User comparator input terminal Not used (fixed at "L")
43	ADDC	I	Connected to the external capacitor for cutting the low band of the ADIP amplifier
44	OPO	O	User operational amplifier output terminal Not used (open)
45	OPN	I	User operational amplifier inversion input terminal Not used (fixed at "L")
46	RFO	O	RF signal output terminal
47	MORFI	I	Receives a MO RF signal in AC coupling
48	MORFO	O	MO RF signal output terminal

• **BD BOARD IC121 CXD2656R**
(DIGITAL SIGNAL PROCESSOR, DIGITAL SERVO PROCESSOR, EFM/ACIRC ENCODER/DECODER, SHOCK PROOF MEMORY CONTROLLER, ATRAC ENCODER/DECODER)

Pin No.	Pin Name	I/O	Description
1	MNT0 (FOK)	O	Focus OK signal output to the system controller (IC501) "H" is output when focus is on ("L": NG)
2	MNT1 (SHOCK)	O	Track jump detection signal output to the system controller (IC501)
3	MNT2 (XBUSY)	O	Busy monitor signal output to the system controller (IC501)
4	MNT3 (SLOCK)	O	Spindle servo lock status monitor signal output to the system controller (IC501)
5	SWDT	I	Writing serial data signal input from the system controller (IC501)
6	SCLK	I (S)	Serial data transfer clock signal input from the system controller (IC501)
7	XLAT	I (S)	Serial data latch pulse signal input from the system controller (IC501)
8	SRDT	O (3)	Reading serial data signal output to the system controller (IC501)
9	SENS	O (3)	Internal status (SENSE) output to the system controller (IC501)
10	$\overline{\text{XRST}}$	I (S)	Reset signal input from the system controller (IC501) "L": reset
11	SQSY	O	Subcode Q sync (SCOR) output to the system controller (IC501) "L" is output every 13.3 msec Almost all, "H" is output
12	DQSY	O	Digital In U-bit CD format subcode Q sync (SCOR) output to the system controller (IC501) "L" is output every 13.3 msec Almost all, "H" is output
13	RECP	I	Laser power selection signal input from the system controller (IC501) "L": playback mode, "H": recording mode
14	XINT	O	Interrupt status output to the system controller (IC501)
15	TX	I	Recording data output enable signal input from the system controller (IC501) Writing data transmission timing input (Also serves as the magnetic head on/off output)
16	OSCI	I	System clock signal (45.158 MHz) input terminal
17	OSCO	O	System clock signal (512Fs=22.5792 MHz) output terminal Not used (open)
18	XTSL	I	Input terminal for the system clock frequency setting "L": 45.1584 MHz, "H": 22.5792 MHz (fixed at "H" in this set)
19	DIN0	I	Digital audio signal input terminal when recording mode (for digital optical input)
20	DIN1	I	Digital audio signal input terminal when recording mode (for digital coaxial input)
21	DOUT	O	Digital audio signal output terminal when playback mode (for digital optical output)
22	DATAI	I	Serial data input terminal Not used (fixed at "L")
23	LRCKI	I	L/R sampling clock signal (44.1 kHz) input terminal Not used (fixed at "L")
24	XBCKI	I	Bit clock signal (2.8224 MHz) input terminal Not used (fixed at "L")
25	ADDT	I	Recording data input from the A/D, D/A converter (IC321)
26	DADT	O	Playback data output to the A/D, D/A converter (IC321)
27	LRCK	O	L/R sampling clock signal (44.1 kHz) output to the A/D, D/A converter (IC321)
28	XBCK	O	Bit clock signal (2.8224 MHz) output to the A/D, D/A converter (IC321)
29	FS256	O	Clock signal (11.2896 MHz) output terminal Not used (open)
30	DVDD	—	Power supply terminal (+3.3V) (digital system)
31 to 34	A03 to A00	O	Address signal output to the D-RAM (IC124)
35	A10	O	Address signal output to the external D-RAM Not used (open)
36 to 40	A04 to A08	O	Address signal output to the D-RAM (IC124)
41	A11	O	Address signal output to the external D-RAM Not used (open)
42	DVSS	—	Ground terminal (digital system)
43	$\overline{\text{XOE}}$	O	Output enable signal output to the D-RAM (IC124) "L" active
44	$\overline{\text{XCAS}}$	O	Column address strobe signal output to the D-RAM (IC124) "L" active
45	A09	O	Address signal output to the D-RAM (IC124)

* I (S) stands for schmitt input, I (A) for analog input, O (3) for 3-state output, and O (A) for analog output in the column I/O.

Pin No.	Pin Name	I/O	Description
46	$\overline{\text{XRAS}}$	O	Row address strobe signal output to the D-RAM (IC124) "L" active
47	$\overline{\text{XWE}}$	O	Write enable signal output to the D-RAM (IC124) "L" active
48	D1	I/O	Two-way data bus with the D-RAM (IC124)
49	D0	I/O	
50	D2	I/O	
51	D3	I/O	
52	MVCI	I (S)	Digital in PLL oscillation input from the external VCO Not used (fixed at "L")
53	ASYO	O	Playback EFM full-swing output terminal
54	ASYI	I (A)	Playback EFM asymmetry comparator voltage input terminal
55	AVDD	—	Power supply terminal (+3.3V) (analog system)
56	BIAS	I (A)	Playback EFM asymmetry circuit constant current input terminal
57	RFI	I (A)	Playback EFM RF signal input from the CXA2523AR (IC101)
58	AVSS	—	Ground terminal (analog system)
59	PCO	O (3)	Phase comparison output for master clock of the recording/playback EFM master PLL
60	FILI	I (A)	Filter input for master clock of the recording/playback master PLL
61	FILO	O (A)	Filter output for master clock of the recording/playback master PLL
62	CLTV	I (A)	Internal VCO control voltage input of the recording/playback master PLL
63	PEAK	I (A)	Light amount signal (RF/ABCD) peak hold input from the CXA2523AR (IC101)
64	BOTM	I (A)	Light amount signal (RF/ABCD) bottom hold input from the CXA2523AR (IC101)
65	ABCD	I (A)	Light amount signal (ABCD) input from the CXA2523AR (IC101)
66	FE	I (A)	Focus error signal input from the CXA2523AR (IC101)
67	AUX1	I (A)	Auxiliary signal (I_3 signal/temperature signal) input from the CXA2523AR (IC101)
68	VC	I (A)	Middle point voltage (+1.65V) input from the CXA2523AR (IC101)
69	ADIO	O (A)	Monitor output of the A/D converter input signal Not used (open)
70	AVDD	—	Power supply terminal (+3.3V) (analog system)
71	ADRT	I (A)	A/D converter operational range upper limit voltage input terminal (fixed at "H" in this set)
72	ADRB	I (A)	A/D converter operational range lower limit voltage input terminal (fixed at "L" in this set)
73	AVSS	—	Ground terminal (analog system)
74	SE	I (A)	Sled error signal input from the CXA2523AR (IC101)
75	TE	I (A)	Tracking error signal input from the CXA2523AR (IC101)
76	DCHG	I (A)	Connected to the +3.3V power supply
77	APC	I (A)	Error signal input for the laser automatic power control Not used (fixed at "H")
78	ADFG	I (S)	ADIP duplex FM signal (22.05 kHz ± 1 kHz) input from the CXA2523AR (IC101)
79	F0CNT	O	Filter f0 control signal output to the CXA2523AR (IC101)
80	XLRF	O	Serial data latch pulse signal output to the CXA2523AR (IC101)
81	CKRF	O	Serial data transfer clock signal output to the CXA2523AR (IC101)
82	DTRF	O	Writing serial data output to the CXA2523AR (IC101)
83	APCREF	O	Control signal output to the reference voltage generator circuit for the laser automatic power control
84	LDDR	O	PWM signal output for the laser automatic power control Not used (open)
85	TRDR	O	Tracking servo drive PWM signal (–) output to the BH6511FS (IC152)
86	TFDR	O	Tracking servo drive PWM signal (+) output to the BH6511FS (IC152)
87	DVDD	—	Power supply terminal (+3.3V) (digital system)
88	FFDR	O	Focus servo drive PWM signal (+) output to the BH6511FS (IC152)
89	FRDR	O	Focus servo drive PWM signal (–) output to the BH6511FS (IC152)
90	FS4	O	Clock signal (176.4 kHz) output terminal (X'tal system) Not used (open)

* I (S) stands for schmitt input, I (A) for analog input, O (3) for 3-state output, and O (A) for analog output in the column I/O.

Pin No.	Pin Name	I/O	Description
91	SRDR	O	Sled servo drive PWM signal (–) output to the BH6511FS (IC152)
92	SFDR	O	Sled servo drive PWM signal (+) output to the BH6511FS (IC152)
93	SPRD	O	Spindle servo drive PWM signal (–) output to the BH6511FS (IC152)
94	SPFD	O	Spindle servo drive PWM signal (+) output to the BH6511FS (IC152)
95	FGIN	I (S)	Input terminal for the test (fixed at “L”)
96	TEST1	I	
97	TEST2	I	
98	TEST3	I	
99	DVSS	—	Ground terminal (digital system)
100	EFMO	O	EFM signal output terminal when recording mode

* I (S) stands for schmitt input, I (A) for analog input, O (3) for 3-state output, and O (A) for analog output in the column I/O.

• **MAIN BOARD IC501 M30624MG-223FP (SYSTEM CONTROLLER)**

Pin No.	Pin Name	I/O	Description
1, 2	NC	O	Not used (open)
3	C1	O	Monitor output terminal for the test C1 error rate is output when test mode
4	ADER	O	Monitor output terminal for the test ADER is output when test mode
5	SQSY	I	Subcode Q sync (SCOR) input from the CXD2656R (IC121) "L" is input every 13.3 msec Almost all, "H" is input
6	RMC	I	Remote control signal input from the remote control receiver (IC761)
7	A1 IN	I	Sircs remote control signal input of the CONTROL A1 II
8	BYTE	I	External data bus line byte selection signal input "L": 16 bit, "H": 8 bit (fixed at "L")
9	CNVSS	—	Ground terminal
10	XT-IN	I	Sub system clock input terminal (32.768 kHz) Not used (open)
11	XT-OUT	O	Sub system clock output terminal (32.768 kHz) Not used (open)
12	$\overline{\text{S.RST}}$	I	System reset signal input from the LA5632 (IC431) and RESET switch (S401) "L": reset For several hundreds msec. after the power supply rises, "L" is input, then it changes to "H"
13	XOUT	O	Main system clock output terminal (10 MHz)
14	GND	—	Ground terminal
15	XIN	I	Main system clock input terminal (10 MHz)
16	+3.3V	—	Power supply terminal (+3.3V)
17	NMI	I	Non-maskable interrupt input terminal (fixed at "H" in this set)
18	DQSY	I	Digital In U-bit CD format subcode Q sync (SCOR) input from the CXD2656R (IC121) "L" is input every 13.3 msec Almost all, "H" is input
19	P.DOWN	I	Power down detection signal input terminal "L": power down, normally: "H"
20	KEYBOARD CLK	I	Not used (fixed at "L")
21	KEYBOARD DATA	I	Not used (fixed at "L")
22	NC	O	Not used (open)
23	XINT	I	Interrupt status input from the CXD2656R (IC121)
24 to 26	NC	O	Not used (open)
27	KEYBOARD CONT	O	Not used (pull down)
28 to 30	NC	O	Not used (open)
31	SWDT	O	Writing data output to the CXD2656R (IC121) and A/D, D/A converter (IC321)
32	SRDT	I	Reading data input from the CXD2656R (IC121)
33	SCLK	O	Serial clock signal output to the CXD2656R (IC121) and A/D, D/A converter (IC321)
34	FLCS	O	Chip select signal output to the FL/LED driver (IC771)
35	FLDATA	O	Serial data output to the FL/LED driver (IC771)
36	NC	O	Not used (open)
37	FLCLK	O	Serial data transfer clock signal output to the FL/LED driver (IC771)
38	DVOL1	I	Jog dial pulse input from the rotary encoder (RV760 REC LEVEL) (B phase input)
39	DVOL0	I	Jog dial pulse input from the rotary encoder (RV760 REC LEVEL) (A phase input)
40	ADA LATCH	O	Serial data latch pulse signal output to the A/D, D/A converter (IC321)
41	NC	I	Not used (fixed at "L")
42	JOG1	I	Jog dial pulse input from the rotary encoder (S713 ⏮ AMS ⏭) (B phase input)
43	JOG0	I	Jog dial pulse input from the rotary encoder (S713 ⏮ AMS ⏭) (A phase input)
44	NC	O	Not used (open)
45	A1 OUT	O	Sircs remote control signal output of the CONTROL A1 II
46	NC	I	Not used (fixed at "H")
47	NC	O	Not used (open)
48	$\overline{\text{DA RST}}$	O	Reset signal output to the A/D, D/A converter (IC321) "L": reset

Pin No.	Pin Name	I/O	Description
49	MUTE	O	Audio line muting on/off control signal output terminal "L": line muting on
50	STB	O	Strobe signal output to the power supply circuit "L": standby mode, "H": power on
51	CHACK IN	I	Detection input from the disc chucking-in detect switch "L": chucking Not used (fixed at "H")
52	NC	O	Not used (open)
53	PACK-OUT	I	Detection input from the loading-out detect switch (S602) "L" at a load-out position, others: "H"
54	LDIN	O	Motor control signal output to the loading motor driver (IC471) "L" active *1
55	LDOUT	O	Motor control signal output to the loading motor driver (IC471) "L" active *1
56	LD-LOW	O	Loading motor drive voltage control signal output for the loading motor driver (IC471) "H" active
57, 58	NC	O	Not used (open)
59	REC-P	I	Detection input from the recording position detect switch (S601) "L" active
60	PB-P	I	Detection input from the playback position detect switch (S604) "L" active
61	REC/PB	I	Not used (fixed at "L")
62	+3.3V	—	Power supply terminal (+3.3V)
63	NC	O	Not used (open)
64	GND	—	Ground terminal
65	SDA	I/O	Two-way data bus with the EEPROM (IC171)
66	MNT3 (SLOCK)	I	Spindle servo lock status monitor signal input from the CXD2656R (IC121)
67	WR-PWR	O	Laser power select signal output to the CXD2656R (IC121) and HF module switch circuit "L": playback mode, "H": recording mode
68	PROTECT	I	Rec-proof claw detect input from the protect detect switch (S102) "H": write protect
69	REFLECT	I	Detection input from the disc reflection rate detect switch (S102) "L": high reflection rate disc, "H": low reflection rate disc
70	LDON	O	Laser diode on/off control signal output to the automatic power control circuit "H": laser on
71	SENS	I	Internal status (SENSE) input from the CXD2656R (IC121)
72	MNT1 (SHOCK)	I	Track jump detection signal input from the CXD2656R (IC121)
73	$\overline{\text{DIG-RST}}$	O	Reset signal output to the CXD2656R (IC121) and BH6511FS (IC152) "L": reset
74	MNT2 (XBUSY)	I	Busy signal input from the CXD2656R (IC121)
75	XLATCH	O	Serial data latch pulse signal output to the CXD2656R (IC121)
76	MOD	O	Laser modulation select signal output to the HF module switch circuit Stop: "L", Playback power: "H", Recording power: 
77	LIMIT-IN	I	Detection input from the sled limit-in detect switch (S101) The optical pick-up is inner position when "L"

*1 Loading motor (M103) control

Terminal \ Mode	LOADING	EJECT	BRAKE	RUN IDLE
LDIN (pin ⑭)	"L"	"H"	"L"	"H"
LDOUT (pin ⑮)	"H"	"L"	"L"	"H"

Pin No.	Pin Name	I/O	Description
78	MNT0 (FOK)	I	Focus OK signal input from the CXD2656R (IC121) “H” is input when focus is on (“L”: NG)
79	SCL	O	Clock signal output to the EEPROM (IC171)
80	SCTX	O	Recording data output enable signal output to the CXD2656R (IC121) and overwrite head driver (IC181) Writing data transmission timing output (Also serves as the magnetic head on/off output)
81	CLOCK SET0	I	Destination setting terminal (fixed at “H” in this set)
82	CLOCK SET1	I	Destination setting terminal (fixed at “L” in this set)
83	LED0	O	LED drive signal output terminal Not used (open)
84	LED1	O	LED drive signal output terminal Not used (open)
85, 86	NC	O	Not used (open)
87	MODEL SEL0	I	Setting terminal for the model (fixed at “L” in this set)
88	MODEL SEL1	I	Setting terminal for the model (fixed at “H” in this set)
89, 90	NC	O	Not used (open)
91	TIMER	I	TIMER switch (S751) input terminal (A/D input) “L”: PLAY, “H”: REC (OFF: center voltage)
92	SOURCE	I	INPUT switch (S741) input terminal (A/D input)
93	KEY3	I	Key input terminal (A/D input) S731 to S733 (PITCH CONTROL, FILTER, TIME keys input)
94	KEY2	I	Key input terminal (A/D input) S721 to S724 (DISPLAY/CHAR, SCROLL, PLAY MODE, I/⏻ keys input)
95	KEY1	I	Key input terminal (A/D input) S711 to S714 and S716 (MENU/NO, YES, PUSH ENTER, CLEAR, EJECT ⏏ keys input)
96	AVSS	—	Ground terminal
97	KEY0	I	Key input terminal (A/D input) S701 to S706 (REC ● , ■, ▶▶, ◀◀, ▮▮, ▷ keys input)
98	VREF	I	Reference voltage (+3.3V) input terminal (for A/D converter)
99	+3.3V	—	Power supply terminal (+3.3V) (for analog system)
100	MONO/ST	I	REC MODE switch (S746) input terminal “L”: MONO, “H”: STEREO

SECTION 7
EXPLODED VIEWS

NOTE:
- -XX and -X mean standardized parts, so they may have some difference from the original one.
- Color Indication of Appearance Parts
  Example:
  KNOB, BALANCE (WHITE) . . . (RED)
  ↑ ↑
  Parts Color Cabinet's Color
- Items marked "*" are not stocked since they are seldom required for routine service. Some delay should be anticipated when ordering these items.
- The mechanical parts with no reference number in the exploded views are not supplied.
- Hardware (# mark) list and accessories and packing materials are given in the last of the electrical parts list.

The components identified by mark ⚠ or dotted line with mark ⚠ are critical for safety.
Replace only with part number specified.

(1) CHASSIS SECTION



Ref. No.	Part No.	Description	Remark
1	1-783-138-11	WIRE (FLAT TYPE) (19 CORE)	
* 2	3-644-407-00	CLIP, AC WIRE E	
3	3-704-515-21	SCREW (BV/RING)	
4	1-783-139-11	WIRE (FLAT TYPE) (21 CORE)	
5	4-210-291-01	SCREW (CASE 3 TP2) (AEP)	
5	4-210-082-01	SCREW (CASE) (UK)	
6	4-999-839-01	SCREW (+BVTTWH M3), STEP	
7	1-783-140-11	WIRE (FLAT TYPE) (23 CORE)	
8	1-569-972-21	SOCKET, SHORT 2P	
9	4-966-267-11	BUSHING (FBS001), CORD	
⚠10	1-751-275-11	CORD, POWER (AEP)	

Ref. No.	Part No.	Description	Remark
⚠10	1-696-586-21	CORD, POWER (UK)	
11	4-218-445-01	PANEL, BACK	
12	A-4724-660-A	MAIN BOARD, COMPLETE	
13	X-4949-523-1	FOOT ASSY (F50180S)	
14	1-500-051-11	BEAD, FERRITE (WITH CASE)	
15	1-675-018-11	SEIKEI 1 BOARD	
16	4-997-138-02	CASE (4095269)	
17	3-655-653-21	BAND (TAITON), BINDING	
CN997	1-569-499-11	PIN, CONNECTOR 3P	
⚠TR901	1-433-886-11	TRANSFORMER, POWER	

(2) FRONT PANEL SECTION



Ref. No.	Part No.	Description	Remark
51	4-998-590-82	PANEL, FRONT	
52	4-942-568-41	EMBLEM (NO.5), SONY	
53	4-998-607-01	INDICATOR (POWER)	
54	4-950-189-01	KNOB (A) (VOL)	
55	4-998-598-01	WINDOW (DISPLAY)	
56	A-4672-565-A	KNOB (AMS) ASSY	
57	4-951-620-01	SCREW (2.6X8), +BVTP	
58	3-704-515-21	SCREW (BV/RING)	
59	1-673-504-11	HP BOARD	
60	4-998-592-01	BUTTON (POWER)	
61	X-4951-538-1	BUTTON (B7) ASSY	
62	4-218-444-01	BUTTON (BASE-7)	
63	4-996-690-13	LID (CARTRIDGE)	
64	4-976-593-11	SPRING (LID), TORSION	
65	4-998-593-01	BUTTON (EDIT)	
66	1-673-505-11	VOL BOARD	
67	4-998-595-01	KNOB (SLIDE)	
68	A-4724-657-A	PSW BOARD, COMPLETE	
69	A-4724-656-A	DISP BOARD, COMPLETE	
70	4-998-594-01	BUTTON (EJECT)	
71	4-996-689-21	BUTTON (MAIN)	
72	3-354-981-01	SPRING (SUS), RING	
73	X-4951-290-1	BASE ASSY, PANEL	

(3) MECHANISM SECTION (MDM-5D)



Ref. No.	Part No.	Description	Remark
* 201	1-668-111-11	SW BOARD	
* 202	4-996-217-01	CHASSIS	
203	4-996-223-01	INSULATOR (F) (BLACK)	
* 204	4-996-218-01	BRACKET (GUIDE R)	
205	4-996-277-01	SPRING (O/C), TENSION	
206	4-996-226-01	LEVER (O/C)	
207	4-999-347-01	INSULATOR (R) (GREEN)	
* 208	4-996-225-01	BRACKET (GUIDE L)	
209	4-988-466-21	SPRING (ELECTROSTATIC), LEAF	
210	4-996-219-01	GEAR (CAM GEAR)	
211	4-996-220-01	GEAR (A)	
212	4-996-221-01	GEAR (B)	
213	4-933-134-01	SCREW (+PTPWH M2.6X6)	
214	4-996-224-01	SCREW (1.7X3), +PWH	

Ref. No.	Part No.	Description	Remark
215	4-996-227-01	LEVER (HEAD)	
216	4-996-229-01	SPRING (HEAD LEVER), TORSION	
217	4-996-212-01	LEVER (LIMITTER)	
218	4-996-213-01	SPRING (LIMITTER), TORSION	
219	4-996-214-01	SPRING (SLIDER), TENSION	
220	4-996-216-01	SPRING (HOLDER), TENSION	
221	4-210-396-01	SPRING (LOCK), TENSION	
222	X-4949-246-1	SLIDER ASSY	
* 223	X-4949-245-7	HOLDER ASSY	
* 224	4-996-211-01	SLIDER (CAM)	
225	4-998-763-01	SPRING (SHUTTER), LEAF	
226	A-4680-118-I	HOLDER COMPLETE ASSY	
M103	X-4949-264-1	MOTOR ASSY, LOADING	

(4) BASE UNIT SECTION (MBU-5D)



The components identified by mark ⚠ or dotted line with mark ⚠ are critical for safety. Replace only with part number specified.

Ref. No.	Part No.	Description	Remark
251	A-4724-637-A	BD BOARD, COMPLETE	
252	3-372-761-01	SCREW (M1.7), TAPPING	
* 253	4-996-267-01	BASE (BU-D)	
* 254	4-996-255-01	BASE (BU-C)	
255	4-900-590-01	SCREW, PRECISION SMALL	
256	4-996-258-01	SPRING, COMPRESSION	
257	4-996-262-01	GEAR (SL-C)	
258	1-667-954-11	FLEXIBLE BOARD	
* 259	4-210-664-01	BASE (BU-A)	
⚠260	A-4672-541-A	OPTICAL PICK-UP KMS-260B/J1RP	
* 261	4-996-252-01	CHASSIS, BU	
* 262	4-996-254-01	BASE (BU-B)	
263	4-967-688-11	MAGNET, ABSORPTION	
264	4-996-260-01	GEAR (SL-A)	

Ref. No.	Part No.	Description	Remark
265	4-996-261-01	GEAR (SL-B)	
266	4-996-264-01	SPRING (SHAFT), LEAF	
267	4-996-265-01	SHAFT, MAIN	
268	4-996-256-01	SL (BASE)	
269	4-996-257-01	RACK (SL)	
270	4-996-263-01	SPRING (CLV), TORSION	
271	4-988-560-01	SCREW (+P 1.7X6)	
272	4-211-036-01	SCREW (1.7X2.5), +PWH	
HR901	1-500-502-11	HEAD, OVER WRITE	
M101	A-4672-475-A	MOTOR ASSY, SPINDLE	
M102	A-4672-474-A	MOTOR ASSY, SLED	
S102	1-762-148-21	SWITCH, PUSH (2 KEY) (REFLECT DET, PROTECT DET)	

SECTION 8
ELECTRICAL PARTS LIST

BD

NOTE:
- Due to standardization, replacements in the parts list may be different from the parts specified in the diagrams or the components used on the set.
- -XX and -X mean standardized parts, so they may have some difference from the original one.
- RESISTORS
  All resistors are in ohms.
  METAL: Metal-film resistor.
  METAL OXIDE: Metal oxide-film resistor.
  F: nonflammable
- Items marked "*" are not stocked since they are seldom required for routine service.
  Some delay should be anticipated when ordering these items.
- SEMICONDUCTORS
  In each case, u: µ, for example:
  uA. . : µA. . uPA. . : µPA. .
  uPB. . : µPB. . uPC. . : µPC. .
  uPD. . : µPD. .
- CAPACITORS
  uF: µF
- COILS
  uH: µH

The components identified by mark ⚠ or dotted line with mark ⚠ are critical for safety.
Replace only with part number specified.

When indicating parts by reference number, please include the board.

Ref. No.	Part No.	Description			Remark
	A-4724-637-A	BD BOARD, COMPLETE			
		**********			
		< CAPACITOR >			
C101	1-125-822-11	TANTALUM	10uF	20%	10V
C102	1-163-038-00	CERAMIC CHIP	0.1uF		25V
C103	1-125-822-11	TANTALUM	10uF	20%	10V
C104	1-125-822-11	TANTALUM	10uF	20%	10V
C105	1-163-021-11	CERAMIC CHIP	0.01uF	10%	50V
C106	1-163-275-11	CERAMIC CHIP	0.001uF	5%	50V
C107	1-163-038-00	CERAMIC CHIP	0.1uF		25V
C108	1-163-038-00	CERAMIC CHIP	0.1uF		25V
C109	1-163-037-11	CERAMIC CHIP	0.022uF	10%	25V
C111	1-164-344-11	CERAMIC CHIP	0.068uF	10%	25V
C112	1-163-017-00	CERAMIC CHIP	0.0047uF	5%	50V
C113	1-109-982-11	CERAMIC CHIP	1uF	10%	10V
C115	1-164-489-11	CERAMIC CHIP	0.22uF	10%	16V
C116	1-163-037-11	CERAMIC CHIP	0.022uF	10%	25V
C117	1-163-809-11	CERAMIC CHIP	0.047uF	10%	25V
C118	1-163-038-00	CERAMIC CHIP	0.1uF		25V
C119	1-125-822-11	TANTALUM	10uF	20%	10V
C121	1-125-822-11	TANTALUM	10uF	20%	10V
C122	1-163-021-11	CERAMIC CHIP	0.01uF	10%	50V
C123	1-163-038-00	CERAMIC CHIP	0.1uF		25V
C124	1-163-038-00	CERAMIC CHIP	0.1uF		25V
C127	1-163-038-00	CERAMIC CHIP	0.1uF		25V
C128	1-163-021-11	CERAMIC CHIP	0.01uF	10%	50V
C129	1-107-823-11	CERAMIC CHIP	0.47uF	10%	16V
C130	1-163-251-11	CERAMIC CHIP	100PF	5%	50V
C131	1-163-023-00	CERAMIC CHIP	0.015uF	5%	50V
C132	1-107-823-11	CERAMIC CHIP	0.47uF	10%	16V
C133	1-163-017-00	CERAMIC CHIP	0.0047uF	5%	50V
C134	1-163-038-00	CERAMIC CHIP	0.1uF		25V
C135	1-163-038-00	CERAMIC CHIP	0.1uF		25V
C136	1-126-206-11	ELECT CHIP	100uF	20%	6.3V
C142	1-163-251-11	CERAMIC CHIP	100PF	5%	50V
C143	1-163-251-11	CERAMIC CHIP	100PF	5%	50V
C144	1-163-251-11	CERAMIC CHIP	100PF	5%	50V
C146	1-163-038-00	CERAMIC CHIP	0.1uF		25V
C151	1-126-206-11	ELECT CHIP	100uF	20%	6.3V
C152	1-163-038-00	CERAMIC CHIP	0.1uF		25V
C153	1-163-021-11	CERAMIC CHIP	0.01uF	10%	50V
C156	1-163-038-00	CERAMIC CHIP	0.1uF		25V
C158	1-163-019-00	CERAMIC CHIP	0.0068uF	10%	50V
C160	1-104-601-11	ELECT CHIP	10uF	20%	10V
C161	1-104-601-11	ELECT CHIP	10uF	20%	10V
C163	1-163-021-11	CERAMIC CHIP	0.01uF	10%	50V
C164	1-163-021-11	CERAMIC CHIP	0.01uF	10%	50V
C167	1-163-038-00	CERAMIC CHIP	0.1uF		25V
C168	1-163-038-00	CERAMIC CHIP	0.1uF		25V
C169	1-125-822-11	TANTALUM	10uF	20%	10V
C171	1-163-038-00	CERAMIC CHIP	0.1uF		25V
C181	1-104-913-11	TANTALUM CHIP	10uF	20%	16V
C183	1-163-038-00	CERAMIC CHIP	0.1uF		25V
C184	1-117-970-11	ELECT CHIP	22uF	20%	10V
C185	1-164-611-11	CERAMIC CHIP	0.001uF	10%	500V
C187	1-104-913-11	TANTALUM CHIP	10uF	20%	16V
C188	1-163-021-11	CERAMIC CHIP	0.01uF	10%	50V
C189	1-163-989-11	CERAMIC CHIP	0.033uF	10%	25V
C190	1-126-206-11	ELECT CHIP	100uF	20%	6.3V
C191	1-163-038-00	CERAMIC CHIP	0.1uF		25V
C196	1-163-038-00	CERAMIC CHIP	0.1uF		25V
C197	1-163-038-00	CERAMIC CHIP	0.1uF		25V
		< CONNECTOR >			
CN101	1-569-479-21	CONNECTOR, FPC 21P			
CN102	1-784-833-21	CONNECTOR, FFC (LIF(NON-ZIF)) 21P			
CN103	1-784-834-21	CONNECTOR, FFC (LIF(NON-ZIF)) 23P			
CN104	1-770-687-11	CONNECTOR, FFC/FPC 4P			
CN110	1-695-440-21	PIN, CONNECTOR (PC BOARD) 6P			
		< DIODE >			
D101	8-719-988-61	DIODE 1SS355TE-17			
D181	8-719-046-86	DIODE F1J6TP			
D183	8-719-046-86	DIODE F1J6TP			
		< IC >			
IC101	8-752-080-95	IC CXA2523AR			
IC103	8-729-903-10	TRANSISTOR FMW1-T-148			
IC121	8-752-390-16	IC CXD2656R			
IC123	8-759-096-87	IC TC7WU04FU (TE12R)			
IC124	8-759-334-38	IC MSM51V4400-70TS-K			
IC152	8-759-430-25	IC BH6511FS-E2			
IC171	8-759-487-04	IC BR24C02F-E2			
IC181	8-759-481-17	IC MC74ACT08DTR2			
IC192	8-759-460-72	IC BA033FP-E2			

BD **DISP**

Ref. No.	Part No.	Description			Remark
		< COIL/FERRITE BEAD/SHORT >			
L101	1-414-813-11	FERRITE	0uH		
L102	1-414-813-11	FERRITE	0uH		
L103	1-414-813-11	FERRITE	0uH		
L105	1-414-813-11	FERRITE	0uH		
L106	1-414-813-11	FERRITE	0uH		
L121	1-414-813-11	FERRITE	0uH		
L122	1-414-813-11	FERRITE	0uH		
L151	1-412-029-11	INDUCTOR CHIP	10uH		
L152	1-412-029-11	INDUCTOR CHIP	10uH		
L153	1-412-032-11	INDUCTOR CHIP	100uH		
L154	1-412-032-11	INDUCTOR CHIP	100uH		
L161	1-414-813-11	FERRITE	0uH		
L162	1-414-813-11	FERRITE	0uH		
L181	1-216-295-91	SHORT	0		
		< TRANSISTOR >			
Q101	8-729-028-91	TRANSISTOR RT1P441M-TP-1			
Q102	8-729-026-53	TRANSISTOR 2SA1576A-T106-QR			
Q103	8-729-028-99	TRANSISTOR RN1307-TE85L			
Q103	8-729-028-99	TRANSISTOR DTC114YUT106			
Q104	8-729-028-99	TRANSISTOR RN1307-TE85L			
Q162	8-729-101-07	TRANSISTOR 2SB798-T1DK			
Q163	8-729-028-91	TRANSISTOR DTA144EUA-T106			
Q181	8-729-018-75	FET 2SJ278MYTR			
Q182	8-729-017-65	FET 2SK1764KYTR			
		< RESISTOR >			
R103	1-216-049-11	RES, CHIP	1K	5%	1/10W
R104	1-216-073-00	METAL CHIP	10K	5%	1/10W
R105	1-216-065-00	RES, CHIP	4.7K	5%	1/10W
R106	1-216-133-00	METAL CHIP	3.3M	5%	1/10W
R107	1-216-113-00	METAL CHIP	470K	5%	1/10W
R109	1-216-295-00	SHORT	0		
R110	1-216-073-00	METAL CHIP	10K	5%	1/10W
R111	1-216-295-00	SHORT	0		
R112	1-216-089-00	RES, CHIP	47K	5%	1/10W
R113	1-216-049-11	RES, CHIP	1K	5%	1/10W
R115	1-216-049-11	RES, CHIP	1K	5%	1/10W
R117	1-216-113-00	METAL CHIP	470K	5%	1/10W
R120	1-216-025-00	RES, CHIP	100	5%	1/10W
R121	1-216-097-00	RES, CHIP	100K	5%	1/10W
R123	1-216-295-00	SHORT	0		
R124	1-216-025-00	RES, CHIP	100	5%	1/10W
R125	1-216-025-00	RES, CHIP	100	5%	1/10W
R127	1-216-025-00	RES, CHIP	100	5%	1/10W
R129	1-216-295-00	SHORT	0		
R131	1-216-073-00	METAL CHIP	10K	5%	1/10W
R132	1-216-097-00	RES, CHIP	100K	5%	1/10W
R133	1-216-117-00	METAL CHIP	680K	5%	1/10W
R134	1-216-049-11	RES, CHIP	1K	5%	1/10W
R135	1-216-061-00	METAL CHIP	3.3K	5%	1/10W
R136	1-216-049-11	RES, CHIP	1K	5%	1/10W
R137	1-216-295-00	SHORT	0		
R140	1-216-029-00	METAL CHIP	150	5%	1/10W
R142	1-216-073-00	METAL CHIP	10K	5%	1/10W
R143	1-216-073-00	METAL CHIP	10K	5%	1/10W
R144	1-216-025-00	RES, CHIP	100	5%	1/10W

Ref. No.	Part No.	Description			Remark
R145	1-216-073-00	METAL CHIP	10K	5%	1/10W
R146	1-216-037-00	METAL CHIP	330	5%	1/10W
R147	1-216-025-00	RES, CHIP	100	5%	1/10W
R148	1-216-045-00	METAL CHIP	680	5%	1/10W
R149	1-216-073-00	METAL CHIP	10K	5%	1/10W
R150	1-216-295-00	SHORT	0		
R151	1-216-073-00	METAL CHIP	10K	5%	1/10W
R152	1-216-073-00	METAL CHIP	10K	5%	1/10W
R158	1-216-097-00	RES, CHIP	100K	5%	1/10W
R159	1-216-097-00	RES, CHIP	100K	5%	1/10W
R160	1-216-295-00	SHORT	0		
R161	1-216-057-00	METAL CHIP	2.2K	5%	1/10W
R162	1-216-057-00	METAL CHIP	2.2K	5%	1/10W
R163	1-216-057-00	METAL CHIP	2.2K	5%	1/10W
R164	1-216-045-00	METAL CHIP	680	5%	1/10W
R165	1-216-097-00	RES, CHIP	100K	5%	1/10W
R166	1-220-149-11	RES, CHIP	2.2	10%	1/2W
R167	1-216-065-00	RES, CHIP	4.7K	5%	1/10W
R169	1-219-724-11	METAL CHIP	1	1%	1/4W
R170	1-216-073-00	METAL CHIP	10K	5%	1/10W
R171	1-216-073-00	METAL CHIP	10K	5%	1/10W
R173	1-216-121-00	RES, CHIP	1M	5%	1/10W
R175	1-216-065-00	RES, CHIP	4.7K	5%	1/10W
R177	1-216-061-00	METAL CHIP	3.3K	5%	1/10W
R179	1-216-085-00	METAL CHIP	33K	5%	1/10W
R180	1-216-073-00	METAL CHIP	10K	5%	1/10W
R182	1-216-089-00	RES, CHIP	47K	5%	1/10W
R183	1-216-089-00	RES, CHIP	47K	5%	1/10W
R184	1-216-073-00	METAL CHIP	10K	5%	1/10W
R185	1-216-081-00	METAL CHIP	22K	5%	1/10W
R186	1-216-089-00	RES, CHIP	47K	5%	1/10W
R188	1-216-073-00	METAL CHIP	10K	5%	1/10W
R189	1-216-073-00	METAL CHIP	10K	5%	1/10W
R190	1-216-073-00	METAL CHIP	10K	5%	1/10W
R195	1-216-073-00	METAL CHIP	10K	5%	1/10W
R196	1-216-295-00	SHORT	0		
R197	1-216-295-00	SHORT	0		
		< SWITCH >			
S101	1-762-596-21	SWITCH, PUSH (1 KEY) (LIMIT IN)			
S102	1-762-148-21	SWITCH, PUSH (2 KEY) (REFLECT DET, PROTECT DET)			
**********					
	A-4724-656-A	DISP BOARD, COMPLETE			
		**********			
	2-389-320-01	CUSHION			
*	4-996-686-11	HOLDER (FL)			
		< CAPACITOR >			
C700	1-126-154-11	ELECT	47uF	20%	6.3V
C701	1-126-154-11	ELECT	47uF	20%	6.3V
C708	1-162-294-31	CERAMIC	0.001uF	10%	50V
C709	1-162-294-31	CERAMIC	0.001uF	10%	50V
C710	1-164-159-11	CERAMIC	0.1uF		50V
C741	1-164-159-11	CERAMIC	0.1uF		50V
C746	1-164-159-11	CERAMIC	0.1uF		50V

Ref. No.	Part No.	Description			Remark
C761	1-126-154-11	ELECT	47uF	20%	6.3V
C762	1-164-159-11	CERAMIC	0.1uF		50V
C770	1-164-159-11	CERAMIC	0.1uF		50V
C771	1-164-159-11	CERAMIC	0.1uF		50V
C772	1-162-213-31	CERAMIC	39PF	5%	50V
C773	1-162-294-31	CERAMIC	0.001uF	10%	50V
C774	1-162-282-31	CERAMIC	100PF	10%	50V
C775	1-162-282-31	CERAMIC	100PF	10%	50V
C776	1-162-282-31	CERAMIC	100PF	10%	50V
C777	1-164-159-11	CERAMIC	0.1uF		50V
C778	1-164-159-11	CERAMIC	0.1uF		50V
C798	1-126-795-11	ELECT	10uF	20%	50V
C799	1-126-795-11	ELECT	10uF	20%	50V
		< CONNECTOR >			
CN701	1-779-556-11	CONNECTOR, FFC (LIF (NON-ZIF)) 21P			
CN751	1-784-642-11	CONNECTOR, BOARD TO BOARD 11P			
		< FLUORESCENT INDICATOR TUBE >			
FL781	1-517-738-11	INDICATOR TUBE, FLUORESCENT			
		< IC >			
IC761	8-749-013-91	IC GP1UC8X (R)			
IC771	8-759-525-49	IC MSM9201-02GS-K			
		< TRANSISTOR >			
Q781	8-729-620-05	TRANSISTOR 2SC2603TP-EF			
Q782	8-729-620-05	TRANSISTOR 2SC2603TP-EF			
		< RESISTOR >			
R702	1-249-421-11	CARBON	2.2K	5%	1/4W
R703	1-247-843-11	CARBON	3.3K	5%	1/4W
R704	1-249-425-11	CARBON	4.7K	5%	1/4W
R705	1-249-429-11	CARBON	10K	5%	1/4W
R706	1-249-435-11	CARBON	33K	5%	1/4W
R712	1-249-421-11	CARBON	2.2K	5%	1/4W
R713	1-247-843-11	CARBON	3.3K	5%	1/4W
R714	1-249-425-11	CARBON	4.7K	5%	1/4W
R717	1-249-429-11	CARBON	10K	5%	1/4W
R742	1-249-426-11	CARBON	5.6K	5%	1/4W
R743	1-249-425-11	CARBON	4.7K	5%	1/4W
R744	1-247-870-11	CARBON	43K	5%	1/4W
R760	1-249-401-11	CARBON	47	5%	1/4W
R762	1-247-807-31	CARBON	100	5%	1/4W
R770	1-249-417-11	CARBON	1K	5%	1/4W
R771	1-249-417-11	CARBON	1K	5%	1/4W
R772	1-247-843-11	CARBON	3.3K	5%	1/4W
R773	1-247-807-31	CARBON	100	5%	1/4W
R774	1-247-807-31	CARBON	100	5%	1/4W
R775	1-247-807-31	CARBON	100	5%	1/4W
R776	1-247-807-31	CARBON	100	5%	1/4W
R777	1-249-417-11	CARBON	1K	5%	1/4W
R778	1-249-417-11	CARBON	1K	5%	1/4W
R781	1-247-807-31	CARBON	100	5%	1/4W
R782	1-249-441-11	CARBON	100K	5%	1/4W
R783	1-247-807-31	CARBON	100	5%	1/4W
R784	1-249-441-11	CARBON	100K	5%	1/4W

Ref. No.	Part No.	Description			Remark
		< SWITCH/ROTARY ENCODER >			
S701	1-762-875-21	SWITCH, KEYBOARD (REC ●)			
S702	1-762-875-21	SWITCH, KEYBOARD (■)			
S703	1-762-875-21	SWITCH, KEYBOARD (▶▶)			
S704	1-762-875-21	SWITCH, KEYBOARD (◀◀)			
S705	1-762-875-21	SWITCH, KEYBOARD (▮▮)			
S706	1-762-875-21	SWITCH, KEYBOARD (▷)			
S711	1-762-875-21	SWITCH, KEYBOARD (MENU/NO)			
S712	1-762-875-21	SWITCH, KEYBOARD (YES)			
S713	1-475-543-11	ENCODER, ROTARY (⏮ AMS ⏭, PUSH ENTER)			
S714	1-762-875-21	SWITCH, KEYBOARD (CLEAR)			
S716	1-762-875-21	SWITCH, KEYBOARD (EJECT §)			
S741	1-572-625-11	SWITCH, SLIDE (INPUT)			
S746	1-572-624-11	SWITCH, SLIDE (REC MODE)			
**********					
	1-673-504-11	HP BOARD *********			
		< CAPACITOR >			
C793	1-126-933-11	ELECT	100uF	20%	16V
C794	1-126-933-11	ELECT	100uF	20%	16V
C795	1-162-294-31	CERAMIC	0.001uF	10%	50V
C796	1-162-294-31	CERAMIC	0.001uF	10%	50V
C797	1-164-159-11	CERAMIC	0.1uF		50V
C798	1-164-159-11	CERAMIC	0.1uF		50V
		< CONNECTOR >			
* CN790	1-564-708-11	PIN, CONNECTOR (SMALL TYPE) 6P			
		< IC >			
IC790	8-759-634-50	IC M5218AL			
		< JACK >			
J790	1-770-904-11	JACK (LARGE TYPE) (PHONES)			
		< RESISTOR >			
R790	1-247-807-31	CARBON	100	5%	1/4W
R791	1-249-433-11	CARBON	22K	5%	1/4W
R792	1-249-441-11	CARBON	100K	5%	1/4W
R793	1-249-429-11	CARBON	10K	5%	1/4W
R794	1-249-433-11	CARBON	22K	5%	1/4W
R795	1-247-807-31	CARBON	100	5%	1/4W
R796	1-249-433-11	CARBON	22K	5%	1/4W
R797	1-249-441-11	CARBON	100K	5%	1/4W
R798	1-249-429-11	CARBON	10K	5%	1/4W
R799	1-249-433-11	CARBON	22K	5%	1/4W
		< VARIABLE RESISTOR >			
RV790	1-225-582-11	RES, VAR, CARBON 20K/20K (PHONE LEVEL)			
**********					

MAIN

Ref. No.	Part No.	Description			Remark
	A-4724-660-A	MAIN BOARD, COMPLETE			
		**********			
	7-685-646-79	SCREW +BVTP 3X8 TYPE2 N-S			
		< BATTERY >			
BT451	1-528-814-11	BATTERY, LITHIUM SECONDARY			
		< CAPACITOR >			
C101	1-136-356-11	FILM	470PF	5%	50V
C102	1-128-551-11	ELECT	22uF	20%	25V
C103	1-126-933-11	ELECT	100uF	20%	16V
C104	1-128-551-11	ELECT	22uF	20%	25V
C105	1-137-366-11	FILM	0.0022uF	5%	50V
C161	1-137-360-11	FILM	220PF	5%	50V
C165	1-137-358-11	FILM	0.0001uF	5%	50V
C166	1-137-358-11	FILM	0.0001uF	5%	50V
C172	1-137-368-11	FILM	0.0047uF	5%	50V
C173	1-130-471-00	MYLAR	0.001uF	5%	50V
C181	1-128-551-11	ELECT	22uF	20%	25V
C183	1-136-356-11	FILM	470PF	5%	50V
C184	1-126-933-11	ELECT	100uF	20%	16V
C201	1-136-356-11	FILM	470PF	5%	50V
C202	1-128-551-11	ELECT	22uF	20%	25V
C203	1-126-933-11	ELECT	100uF	20%	16V
C204	1-128-551-11	ELECT	22uF	20%	25V
C205	1-137-366-11	FILM	0.0022uF	5%	50V
C261	1-137-360-11	FILM	220PF	5%	50V
C265	1-137-358-11	FILM	0.0001uF	5%	50V
C266	1-137-358-11	FILM	0.0001uF	5%	50V
C272	1-137-368-11	FILM	0.0047uF	5%	50V
C273	1-130-471-00	MYLAR	0.001uF	5%	50V
C281	1-128-551-11	ELECT	22uF	20%	25V
C283	1-136-356-11	FILM	470PF	5%	50V
C284	1-126-933-11	ELECT	100uF	20%	16V
C311	1-164-159-11	CERAMIC	0.1uF		50V
C341	1-102-942-00	CERAMIC	5.0PF	±0.5PF	50V
C342	1-102-942-00	CERAMIC	5.0PF	±0.5PF	50V
C345	1-164-159-11	CERAMIC	0.1uF		50V
C346	1-164-159-11	CERAMIC	0.1uF		50V
C347	1-126-933-11	ELECT	100uF	20%	16V
C348	1-126-934-11	ELECT	220uF	20%	10V
C349	1-164-159-11	CERAMIC	0.1uF		50V
C352	1-164-159-11	CERAMIC	0.1uF		50V
C353	1-164-159-11	CERAMIC	0.1uF		50V
C354	1-126-934-11	ELECT	220uF	20%	10V
C355	1-164-159-11	CERAMIC	0.1uF		50V
C356	1-126-933-11	ELECT	100uF	20%	16V
C357	1-164-159-11	CERAMIC	0.1uF		50V
C358	1-164-159-11	CERAMIC	0.1uF		50V
C359	1-164-159-11	CERAMIC	0.1uF		50V
C360	1-164-159-11	CERAMIC	0.1uF		50V
C361	1-126-926-11	ELECT	1000uF	20%	10V
C362	1-162-282-31	CERAMIC	100PF	10%	50V
C363	1-162-282-31	CERAMIC	100PF	10%	50V
C364	1-162-282-31	CERAMIC	100PF	10%	50V
C368	1-126-933-11	ELECT	100uF	20%	16V
C391	1-126-933-11	ELECT	100uF	20%	16V

Ref. No.	Part No.	Description			Remark
C392	1-126-933-11	ELECT	100uF	20%	16V
C401	1-164-159-11	CERAMIC	0.1uF		50V
C402	1-164-159-11	CERAMIC	0.1uF		50V
C403	1-164-159-11	CERAMIC	0.1uF		50V
C411	1-117-850-11	ELECT	15000uF	20%	16V
C413	1-126-952-11	ELECT	1000uF	20%	35V
C415	1-126-952-11	ELECT	1000uF	20%	35V
C421	1-128-563-11	ELECT	100uF	20%	100V
C422	1-164-159-11	CERAMIC	0.1uF		50V
C423	1-126-968-11	ELECT	100uF	20%	50V
C424	1-128-551-11	ELECT	22uF	20%	25V
C425	1-126-968-11	ELECT	100uF	20%	50V
C430	1-164-159-11	CERAMIC	0.1uF		50V
C431	1-104-664-11	ELECT	47uF	20%	25V
C432	1-126-963-11	ELECT	4.7uF	20%	50V
C433	1-126-964-11	ELECT	10uF	20%	50V
C434	1-126-916-11	ELECT	1000uF	20%	6.3V
C435	1-126-964-11	ELECT	10uF	20%	50V
C436	1-164-159-11	CERAMIC	0.1uF		50V
C437	1-164-159-11	CERAMIC	0.1uF		50V
C438	1-126-934-11	ELECT	220uF	20%	10V
C439	1-126-926-11	ELECT	1000uF	20%	10V
C440	1-126-964-11	ELECT	10uF	20%	50V
C472	1-126-933-11	ELECT	100uF	20%	16V
C473	1-162-306-11	CERAMIC	0.01uF	20%	16V
C474	1-162-306-11	CERAMIC	0.01uF	20%	16V
C475	1-126-965-11	ELECT	22uF	20%	50V
C500	1-131-347-00	TANTALUM	1uF	10%	35V
C512	1-164-159-11	CERAMIC	0.1uF		50V
C516	1-164-159-11	CERAMIC	0.1uF		50V
C519	1-162-294-31	CERAMIC	0.001uF	10%	50V
C531	1-162-282-31	CERAMIC	100PF	10%	50V
C533	1-162-282-31	CERAMIC	100PF	10%	50V
C562	1-164-159-11	CERAMIC	0.1uF		50V
C571	1-162-282-31	CERAMIC	100PF	10%	50V
C572	1-162-282-31	CERAMIC	100PF	10%	50V
C573	1-162-282-31	CERAMIC	100PF	10%	50V
C575	1-162-282-31	CERAMIC	100PF	10%	50V
C593	1-162-294-31	CERAMIC	0.001uF	10%	50V
C594	1-162-294-31	CERAMIC	0.001uF	10%	50V
C595	1-162-294-31	CERAMIC	0.001uF	10%	50V
C597	1-162-294-31	CERAMIC	0.001uF	10%	50V
C598	1-164-159-11	CERAMIC	0.1uF		50V
C599	1-164-159-11	CERAMIC	0.1uF		50V
C601	1-162-306-11	CERAMIC	0.01uF	20%	16V
C611	1-164-159-11	CERAMIC	0.1uF		50V
C612	1-162-306-11	CERAMIC	0.01uF	20%	16V
C623	1-126-963-11	ELECT	4.7uF	20%	50V
C631	1-164-159-11	CERAMIC	0.1uF		50V
C661	1-164-159-11	CERAMIC	0.1uF		50V
C851	1-164-159-11	CERAMIC	0.1uF		50V
C852	1-164-159-11	CERAMIC	0.1uF		50V
C853	1-164-159-11	CERAMIC	0.1uF		50V
C854	1-104-646-11	CERAMIC	2.2uF	20%	50V
C855	1-164-159-11	CERAMIC	0.1uF		50V
⚠C901	1-113-920-11	CERAMIC	0.0022uF	20%	250V
⚠C902	1-113-920-11	CERAMIC	0.0022uF	20%	250V

The components identified by mark ⚠ or dotted line with mark ⚠ are critical for safety.
Replace only with part number specified.

Ref. No.	Part No.	Description	Remark
		< CONNECTOR >	
CN341	1-784-418-11	CONNECTOR, FFC (LIF (NON-ZIF)) 21P	
* CN391	1-564-708-11	PIN, CONNECTOR (SMALL TYPE) 6P	
CN421	1-779-287-11	CONNECTOR, FFC (LIF (NON-ZIF)) 19P	
CN451	1-568-683-11	PIN, CONNECTOR (PC BAORD) 2P	
CN500	1-691-765-11	PLUG (MICRO CONNECTOR) 3P	
CN501	1-784-417-11	CONNECTOR, FFC (LIF (NON-ZIF) 23P	
* CN502	1-568-934-11	PIN, CONNECTOR 7P	
* CN901	1-580-230-11	PIN, CONNECTOR (PC BOARD) 2P	
CN999	1-569-490-11	SOCKET, CONNECTOR 3P	
		< DIODE >	
D341	8-719-911-19	DIODE 1SS133T-72	
D342	8-719-911-19	DIODE 1SS133T-72	
D343	8-719-911-19	DIODE 1SS133T-72	
D344	8-719-911-19	DIODE 1SS133T-72	
D411	8-719-024-99	DIODE 11ES2-NTA2B	
D412	8-719-024-99	DIODE 11ES2-NTA2B	
D413	8-719-024-99	DIODE 11ES2-NTA2B	
D414	8-719-024-99	DIODE 11ES2-NTA2B	
D415	8-719-024-99	DIODE 11ES2-NTA2B	
D416	8-719-024-99	DIODE 11ES2-NTA2B	
D421	8-719-024-99	DIODE 11ES2-NTA2B	
D423	8-719-933-65	DIODE HZS11A3LTA	
D431	8-719-911-19	DIODE 1SS133T-72	
D432	8-719-911-19	DIODE 1SS133T-72	
D439	8-719-911-19	DIODE 1SS133T-72	
D451	8-719-024-99	DIODE 11ES2-NTA2B	
D452	8-719-210-21	DIODE 11EQS04-NTA2B	
D453	8-719-911-19	DIODE 1SS133T-72	
D454	8-719-911-19	DIODE 1SS133T-72	
D471	8-719-933-39	DIODE HZS6C1LTA	
D851	8-719-911-19	DIODE 1SS133T-72	
		< GROUND PLATE >	
* EP401	4-962-200-01	PLATE (TR), GROUND	
		< IC >	
IC101	8-759-634-50	IC M5218AL	
IC201	8-759-634-50	IC M5218AL	
IC301	8-759-634-50	IC M5218AL	
IC310	8-759-633-42	IC M5293L	
IC321	8-759-579-68	IC AK4524	
IC322	8-759-917-18	IC TC74HCU04AP	
IC431	8-759-525-48	IC LA5632	
IC471	8-759-822-09	IC LB1641	
IC501	8-759-599-74	IC M30624MG-223FP	
IC601	8-759-917-18	IC TC74HCU04AP	
IC611	8-749-012-70	IC GP1F38R (DIGITAL OPTICAL IN)	
IC661	8-749-012-69	IC GP1F38T (DIGITAL OPTICAL OUT)	
		< JACK >	
J101	1-784-430-11	JACK, PIN 4P (LINE (ANALOG))	
J631	1-784-432-11	JACK, PIN 1P (DIGITAL COAXIAL IN)	
J851	1-779-655-21	JACK (SMALL TYPE) (2 GANG)	(CONTROL A1 II)
		< COIL >	
L341	1-410-324-11	INDUCTOR 4.7uH	
L342	1-410-324-11	INDUCTOR 4.7uH	
L343	1-410-324-11	INDUCTOR 4.7uH	
L345	1-414-747-11	INDUCTOR 0uH	
L346	1-414-793-21	FERRITE 0uH	
L348	1-414-747-11	INDUCTOR 0uH	
L349	1-410-397-21	FERRITE BEAD INDUCTOR	
L350	1-410-397-21	FERRITE BEAD INDUCTOR	
L411	1-414-747-11	INDUCTOR 0uH	
L412	1-414-747-11	INDUCTOR 0uH	
L611	1-410-509-11	INDUCTOR 10uH	
L661	1-410-509-11	INDUCTOR 10uH	
		< LINE FILTER >	
⚠ LF901	1-424-485-11	FILTER, LINE	
		< TRANSISTOR >	
Q187	8-729-044-08	TRANSISTOR 2SD1915 (F)-T (TA).SO	
Q287	8-729-044-08	TRANSISTOR 2SD1915 (F)-T (TA).SO	
Q306	8-729-422-57	TRANSISTOR UN4111-TA	
Q401	8-729-422-57	TRANSISTOR UN4111-TA	
Q402	8-729-422-57	TRANSISTOR UN4111-TA	
Q403	8-729-040-19	TRANSISTOR RT1N137L-TP	
Q404	8-729-040-19	TRANSISTOR RT1N137L-TP	
Q471	8-729-900-80	TRANSISTOR UN4211-TA	
Q472	8-729-119-76	TRANSISTOR 2SA1115TP-EF	
Q851	8-729-620-05	TRANSISTOR 2SC2603TP-EF	
		< RESISTOR >	
R21	1-249-437-11	CARBON 47K 5% 1/4W	
R22	1-249-437-11	CARBON 47K 5% 1/4W	
R82	1-249-429-11	CARBON 10K 5% 1/4W	
R83	1-249-429-11	CARBON 10K 5% 1/4W	
R91	1-249-429-11	CARBON 10K 5% 1/4W	
R92	1-249-429-11	CARBON 10K 5% 1/4W	
R93	1-249-429-11	CARBON 10K 5% 1/4W	
R101	1-249-435-11	CARBON 33K 5% 1/4W	
R102	1-249-431-11	CARBON 15K 5% 1/4W	
R103	1-247-887-00	CARBON 220K 5% 1/4W	
R104	1-260-091-11	CARBON 220 5% 1/2W	
R106	1-249-401-11	CARBON 47 5% 1/4W	
R161	1-249-429-11	CARBON 10K 5% 1/4W	
R162	1-249-429-11	CARBON 10K 5% 1/4W	
R163	1-249-429-11	CARBON 10K 5% 1/4W	
R164	1-249-429-11	CARBON 10K 5% 1/4W	
R165	1-249-433-11	CARBON 22K 5% 1/4W	
R166	1-249-433-11	CARBON 22K 5% 1/4W	
R172	1-249-419-11	CARBON 1.5K 5% 1/4W	
R173	1-249-419-11	CARBON 1.5K 5% 1/4W	
R181	1-249-409-11	CARBON 220 5% 1/4W	
R182	1-249-441-11	CARBON 100K 5% 1/4W	
R183	1-249-411-11	CARBON 330 5% 1/4W	
R187	1-249-429-11	CARBON 10K 5% 1/4W	
R201	1-249-435-11	CARBON 33K 5% 1/4W	

The components identified by mark ⚠ or dotted line with mark ⚠ are critical for safety.
Replace only with part number specified.

MAIN **PSW**

Ref. No.	Part No.	Description			Remark
R202	1-249-431-11	CARBON	15K	5%	1/4W
R203	1-247-887-00	CARBON	220K	5%	1/4W
R204	1-260-091-11	CARBON	220	5%	1/2W
R206	1-249-401-11	CARBON	47	5%	1/4W
R261	1-249-429-11	CARBON	10K	5%	1/4W
R262	1-249-429-11	CARBON	10K	5%	1/4W
R263	1-249-429-11	CARBON	10K	5%	1/4W
R264	1-249-429-11	CARBON	10K	5%	1/4W
R265	1-249-433-11	CARBON	22K	5%	1/4W
R266	1-249-433-11	CARBON	22K	5%	1/4W
R272	1-249-419-11	CARBON	1.5K	5%	1/4W
R273	1-249-419-11	CARBON	1.5K	5%	1/4W
R281	1-249-409-11	CARBON	220	5%	1/4W
R282	1-249-441-11	CARBON	100K	5%	1/4W
R283	1-249-411-11	CARBON	330	5%	1/4W
R287	1-249-429-11	CARBON	10K	5%	1/4W
R341	1-249-424-11	CARBON	3.9K	5%	1/4W
R342	1-247-807-31	CARBON	100	5%	1/4W
R343	1-249-413-11	CARBON	470	5%	1/4W
R344	1-247-807-31	CARBON	100	5%	1/4W
R345	1-247-807-31	CARBON	100	5%	1/4W
R346	1-247-807-31	CARBON	100	5%	1/4W
R347	1-249-401-11	CARBON	47	5%	1/4W
R348	1-249-401-11	CARBON	47	5%	1/4W
R349	1-249-401-11	CARBON	47	5%	1/4W
R350	1-249-401-11	CARBON	47	5%	1/4W
R383	1-247-883-00	CARBON	150K	5%	1/4W
R391	1-260-091-11	CARBON	220	5%	1/2W
R392	1-260-091-11	CARBON	220	5%	1/2W
R421	1-249-385-11	CARBON	2.2	5%	1/6W
R422	1-249-433-11	CARBON	22K	5%	1/4W
R424	1-249-441-11	CARBON	100K	5%	1/4W
R425	1-249-441-11	CARBON	100K	5%	1/4W
R426	1-249-441-11	CARBON	100K	5%	1/4W
R427	1-249-429-11	CARBON	10K	5%	1/4W
R431	1-247-807-31	CARBON	100	5%	1/4W
R432	1-249-416-11	CARBON	820	5%	1/4W
R433	1-249-412-11	CARBON	390	5%	1/4W
R434	1-249-429-11	CARBON	10K	5%	1/4W
R435	1-249-441-11	CARBON	100K	5%	1/4W
R439	1-249-433-11	CARBON	22K	5%	1/4W
R440	1-249-417-11	CARBON	1K	5%	1/4W
R451	1-247-807-31	CARBON	100	5%	1/4W
R472	1-249-434-11	CARBON	27K	5%	1/4W
R473	1-249-429-11	CARBON	10K	5%	1/4W
R474	1-249-429-11	CARBON	10K	5%	1/4W
R475	1-249-417-11	CARBON	1K	5%	1/4W
R500	1-249-429-11	CARBON	10K	5%	1/4W
R505	1-249-429-11	CARBON	10K	5%	1/4W
R506	1-249-429-11	CARBON	10K	5%	1/4W
R513	1-247-903-00	CARBON	1M	5%	1/4W
R519	1-249-429-11	CARBON	10K	5%	1/4W
R521	1-249-429-11	CARBON	10K	5%	1/4W
R522	1-249-429-11	CARBON	10K	5%	1/4W
R531	1-249-429-11	CARBON	10K	5%	1/4W
R532	1-249-429-11	CARBON	10K	5%	1/4W
R533	1-249-429-11	CARBON	10K	5%	1/4W

Ref. No.	Part No.	Description			Remark
R548	1-249-429-11	CARBON	10K	5%	1/4W
R549	1-249-429-11	CARBON	10K	5%	1/4W
R550	1-249-429-11	CARBON	10K	5%	1/4W
R551	1-249-429-11	CARBON	10K	5%	1/4W
R553	1-249-429-11	CARBON	10K	5%	1/4W
R559	1-249-429-11	CARBON	10K	5%	1/4W
R560	1-249-429-11	CARBON	10K	5%	1/4W
R561	1-249-441-11	CARBON	100K	5%	1/4W
R566	1-249-441-11	CARBON	100K	5%	1/4W
R568	1-249-429-11	CARBON	10K	5%	1/4W
R569	1-249-429-11	CARBON	10K	5%	1/4W
R573	1-249-429-11	CARBON	10K	5%	1/4W
R574	1-249-429-11	CARBON	10K	5%	1/4W
R575	1-249-429-11	CARBON	10K	5%	1/4W
R577	1-249-429-11	CARBON	10K	5%	1/4W
R581	1-249-429-11	CARBON	10K	5%	1/4W
R584	1-249-429-11	CARBON	10K	5%	1/4W
R589	1-249-429-11	CARBON	10K	5%	1/4W
R591	1-249-429-11	CARBON	10K	5%	1/4W
R593	1-249-429-11	CARBON	10K	5%	1/4W
R594	1-249-429-11	CARBON	10K	5%	1/4W
R595	1-249-429-11	CARBON	10K	5%	1/4W
R597	1-249-429-11	CARBON	10K	5%	1/4W
R598	1-249-429-11	CARBON	10K	5%	1/4W
R599	1-249-429-11	CARBON	10K	5%	1/4W
R613	1-247-895-00	CARBON	470K	5%	1/4W
R614	1-249-437-11	CARBON	47K	5%	1/4W
R623	1-247-895-00	CARBON	470K	5%	1/4W
R624	1-249-437-11	CARBON	47K	5%	1/4W
R631	1-247-804-11	CARBON	75	5%	1/4W
R632	1-249-417-11	CARBON	1K	5%	1/4W
R634	1-247-891-00	CARBON	330K	5%	1/4W
R635	1-249-438-11	CARBON	56K	5%	1/4W
R636	1-249-417-11	CARBON	1K	5%	1/4W
R851	1-249-426-11	CARBON	5.6K	5%	1/4W
R852	1-249-425-11	CARBON	4.7K	5%	1/4W
R853	1-249-429-11	CARBON	10K	5%	1/4W
R854	1-249-393-11	CARBON	10	5%	1/4W
		< SWITCH >			
S401	1-554-088-00	SWITCH, KEY BOARD (RESET)			
		< TRANSFORMER >			
⚠TR901	1-433-886-11	TRANSFORMER, POWER			
		< VIBRATOR >			
X341	1-760-955-11	VIBRATOR, CRYSTAL (45.1584MHz)			
X513	1-781-174-21	VIBRATOR, CERAMIC (10MHz)			
**********					
	A-4724-657-A	PSW BOARD, COMPLETE			
		**********			
		< CAPACITOR >			
C751	1-164-159-11	CERAMIC	0.1uF		50V

The components identified by mark ⚠ or dotted line with mark ⚠ are critical for safety.
Replace only with part number specified.

Ref. No.	Part No.	Description			Remark
		< CONNECTOR >			
CN750	1-784-641-11	CONNECTOR, BOARD TO BOARD 11P			
		< DIODE >			
D756	8-719-313-43	LED SEL6210S-TH10 (STANDBY)			
D759	8-719-313-45	LED SEL6810A-TH10 (PITCH CONTROL)			
		< TRANSISTOR >			
Q756	8-729-422-57	TRANSISTOR UN4111-TA			
Q759	8-729-422-57	TRANSISTOR UN4111-TA			
		< RESISTOR >			
R722	1-249-421-11	CARBON	2.2K	5%	1/4W
R723	1-247-843-11	CARBON	3.3K	5%	1/4W
R724	1-249-425-11	CARBON	4.7K	5%	1/4W
R732	1-249-421-11	CARBON	2.2K	5%	1/4W
R733	1-247-843-11	CARBON	3.3K	5%	1/4W
R752	1-249-429-11	CARBON	10K	5%	1/4W
R756	1-249-409-11	CARBON	220	5%	1/4W
R759	1-247-807-31	CARBON	100	5%	1/4W
		< SWITCH >			
S721	1-762-875-21	SWITCH, KEYBOARD (DISPLAY/CHAR)			
S722	1-762-875-21	SWITCH, KEYBOARD (SCROLL)			
S723	1-762-875-21	SWITCH, KEYBOARD (PLAY MODE)			
S724	1-762-875-21	SWITCH, KEYBOARD (I/⏻)			
S731	1-762-875-21	SWITCH, KEYBOARD (PITCH CONTROL)			
S732	1-762-875-21	SWITCH, KEYBOARD (REPEAT)			
S733	1-762-875-21	SWITCH, KEYBOARD (TIME)			
S751	1-572-625-11	SWITCH, SLIDE (TIMER)			
**********					
*	1-668-111-11	SW BOARD			
		*********			
		< CONNECTOR >			
* CN601	1-506-486-11	PIN, CONNECTOR 7P			
		< SWITCH >			
S601	1-572-126-21	SWITCH, PUSH (1 KEY) (REC POSITION)			
S602	1-572-126-21	SWITCH, PUSH (1 KEY) (PACK OUT)			
S604	1-771-264-11	SWITCH, PUSH (DETECTION) (1 KEY) (PLAY POSITION)			
**********					
	1-673-505-11	VOL BOARD			
		**********			
		< CAPACITOR >			
C765	1-162-294-31	CERAMIC	0.001uF	10%	50V
C766	1-162-294-31	CERAMIC	0.001uF	10%	50V
		< ROTARY ENCODER >			
RV760	1-418-363-11	ENCODER, ROTARY (REC LEVEL)			
**********					

Ref. No.	Part No.	Description	Remark
		MISCELLANEOUS	
		**********	
1	1-783-138-11	WIRE (FLAT TYPE) (19 CORE)	
4	1-783-139-11	WIRE (FLAT TYPE) (21 CORE)	
7	1-783-140-11	WIRE (FLAT TYPE) (23 CORE)	
8	1-569-972-21	SOCKET, SHORT 2P	
⚠10	1-751-275-11	CORD, POWER (AEP)	
⚠10	1-696-586-21	CORD, POWER (UK)	
14	1-500-051-11	BEAD, FERRITE (WITH CASE)	
15	1-675-018-11	SEIKEI 1 BOARD	
258	1-667-954-11	FLEXIBLE BOARD	
⚠260	A-4672-541-A	OPTICAL PICK-UP KMS-260B/J1RP	
CN997	1-569-499-11	PIN, CONNECTOR 3P	
HR901	1-500-502-11	HEAD, OVER WRITE	
M101	A-4672-475-A	MOTOR ASSY, SPINDLE	
M102	A-4672-474-A	MOTOR ASSY, SLED	
M103	X-4949-264-1	MOTOR ASSY, LOADING	
S102	1-762-148-21	SWITCH, PUSH (2 KEY) (REFLECT DET, PROTECT DET)	
⚠TR901	1-433-886-11	TRANSFORMER, POWER	
**********			
		**********	
		HARDWARE LIST	
		**********	
#1	7-685-871-01	SCREW +BVTP 3X6 (S)	
#2	7-685-885-09	SCREW +BVTT 4X16 (S)	
#3	7-621-772-20	SCREW +B 2X5	
#4	7-621-772-40	SCREW +B 2X8	
#5	7-627-852-08	SCREW, PRECISION +P 1.7X2.5	
#6	7-685-533-19	SCREW +BTP 2.6X6 TYPE2 N-S	
#7	7-685-133-19	SCREW (DIA. 2.6) (IT3B)	
**********			
		ACCESSORIES & PACKING MATERIALS	
		**********	
	1-475-586-11	REMOTE COMMANDER (RM-D15M)	
	1-574-264-11	CORD, LIGHT PLUG	
	1-590-925-31	CORD, CONNECTION	
	3-866-709-11	MANUAL, INSTRUCTION (ENGLISH, FRENCH, SPANISH, PORTUGUESE) (AEP, UK)	
	3-866-709-21	MANUAL, INSTRUCTION (GERMAN, DUTCH, SWEDISH, ITALIAN) (AEP)	
	4-983-537-01	COVER, BATTERY (for RM-D15M)	

The components identified by mark ⚠ or dotted line with mark ⚠ are critical for safety.
Replace only with part number specified.

Sony Corporation
Home Audio Company

99E057548-1
Printed in Hungary © 1999. 5
Published by Quality Assurance Dept.